

EE 637 Final Exam  
May 4, Spring 2004

Name: \_\_\_\_\_

**Instructions:**

- Follow all instructions carefully!
- This is a 120 minute exam containing **five** problems.
- You may **only** use your brain and a pencil (or pen) to complete this exam. You **may not** use your book, notes or a calculator.

**Good Luck.**

Name: \_\_\_\_\_

**Problem 1.**(15pt) Consider an image  $f(x, y)$  with a CSFT given by  $F(u, v)$  and a forward projection

$$\begin{aligned} p_\theta(r) &= \mathcal{FP} \{f(x, y)\} \\ &= \int_{-\infty}^{\infty} f(r \cos(\theta) - z \sin(\theta), r \sin(\theta) + z \cos(\theta)) dz \end{aligned}$$

and let  $P_\theta(\rho)$  denote the CTFT of  $p_\theta(r)$ .

Define the functions

$$\begin{aligned} \delta(x, y) &= \delta(x)\delta(y) \\ \text{rect}(x) &= \begin{cases} 1 & \text{if } |x| \leq 1/2 \\ 0 & \text{if } |x| > 1/2 \end{cases} \end{aligned}$$

a) Calculate the forward projection  $p_\theta(r)$  when

$$f(x, y) = \delta(x - 1, y)$$

b) Calculate the forward projection  $p_\theta(r)$  when

$$f(x, y) = \text{rect} \left( \sqrt{x^2 + y^2} \right)$$

c) Calculate the  $P_\theta(\rho)$  (i.e. the CTFT of  $p_\theta(r)$ ) when

$$f(x, y) = \text{rect} \left( \sqrt{x^2 + y^2} \right)$$

**(Hint:** Use the fact that the CSFT of  $\text{rect}(\sqrt{x^2 + y^2})$  is  $\text{jinc}(u, v)$  )

Name: \_\_\_\_\_

Name: \_\_\_\_\_

**Problem 2.**(30pt) Let  $X(m, n)$  be an achromatic image taking continuous values in the interval  $[0, 1]$ , and let  $T(m, n)$  be a 2-D random field of i.i.d. random variables which are uniformly distributed on the interval  $[0, 1]$ . Let the halftoned version of  $X(m, n)$  be given by

$$Y(m, n) = \begin{cases} 1 & \text{if } X(m, n) \geq T(m, n) \\ 0 & \text{if } X(m, n) < T(m, n) \end{cases}$$

- a) Is  $Y(m, n)$  a stationary random process?
- b) Calculate  $\mu(m, n) = E[Y(m, n)]$
- c) Calculate  $E[D(m, n)D(m+k, n+l)]$  for  $D(m, n) = Y(m, n) - \mu(m, n)$ .
- d) Is  $D(m, n)$  a stationary random process?
- e) For the special case of  $X(m, n) = g$ , compute the power spectral density  $S(e^{j\mu}, e^{j\nu})$  of  $D(m, n)$ .
- f) Is  $Y(m, n)$  a good quality halftone of  $X(m, n)$ . Justify your answer.

Name: \_\_\_\_\_

Name: \_\_\_\_\_

**Problem 3.**(25pt) Consider the following 2-D LSI systems. The first systems has input  $x(m, n)$  and output  $y(m, n)$ , and the second system has input  $y(m, n)$  and output  $z(m, n)$ .

$$y(m, n) = x(m, n) + ay(m, n - 1) \quad \text{S1}$$

$$z(m, n) = y(m, n) + bz(m - 1, n) \quad \text{S2}$$

- a) Calculate the 2-D frequency response  $H_1(e^{j\mu}, e^{j\nu}) = \frac{Y(e^{j\mu}, e^{j\nu})}{X(e^{j\mu}, e^{j\nu})}$ .
- b) Calculate the 2-D frequency response for system  $H_2(e^{j\mu}, e^{j\nu}) = \frac{Z(e^{j\mu}, e^{j\nu})}{Y(e^{j\mu}, e^{j\nu})}$ .
- c) Calculate the 2-D frequency response for system  $H_3(e^{j\mu}, e^{j\nu}) = \frac{Z(e^{j\mu}, e^{j\nu})}{X(e^{j\mu}, e^{j\nu})}$ .
- d) Calculate a single 2-D difference equation for the system  $H_3(e^{j\mu}, e^{j\nu})$ .
- e) For what values of  $a$  and  $b$  is the 2-D system  $H_3(e^{j\mu}, e^{j\nu})$  stable?

Name: \_\_\_\_\_

Name: \_\_\_\_\_

**Problem 4.**(15pt) In a color matching experiment, the three primaries  $R, G, B$  are used to match the color of a pure spectral component at wavelength  $\lambda$ . (Assume that the color matching allows for color to be subtracted from the reference in the standard manner described in class.)

At each wavelength  $\lambda$ , the matching color is given by

$$[R, G, B] \begin{bmatrix} r(\lambda) \\ g(\lambda) \\ b(\lambda) \end{bmatrix}$$

where

$$\begin{aligned} 1 &= \int_0^\infty r(\lambda) d\lambda \\ 1 &= \int_0^\infty g(\lambda) d\lambda \\ 1 &= \int_0^\infty b(\lambda) d\lambda \end{aligned}$$

Further define the white point

$$W = [R, G, B] \begin{bmatrix} r_w \\ g_w \\ b_w \end{bmatrix}$$

Let  $I(\lambda)$  be the light reflected from a surface.

- Calculate  $(r_e, g_e, b_e)$  the tristimulus values for the spectral distribution  $I(\lambda)$  using primaries  $R, G, B$  and an equal energy white point.
- Calculate  $(r_c, g_c, b_c)$  the tristimulus values for the spectral distribution  $I(\lambda)$  using primaries  $R, G, B$  and white point  $(r_w, g_w, b_w)$ .
- Calculate  $(r_\gamma, g_\gamma, b_\gamma)$  the gamma corrected tristimulus values for the spectral distribution  $I(\lambda)$  using primaries  $R, G, B$ , white point  $(r_w, g_w, b_w)$ , and  $\gamma = 2.2$ .



Name: \_\_\_\_\_

**Name:** \_\_\_\_\_

**Problem 5.**(15) Consider the discrete-time signal  $x_n$ , and let  $\hat{x}_n$  be the linear causal prediction of  $x_n$  given by

$$\hat{x}_n = \sum_{k=1}^p a_k x_{n-k}$$

Let the total squared prediction error (TSPE) be given by

$$TSPE = \sum_{n=0}^{N-1} (x_n - \hat{x}_n)^2$$

- a) Determine a formula for the TSPE in terms of the prediction coefficients  $a_k$ .
- b) Compute an expression for the coefficients  $a_k$  that minimize the TSPE.
- c) Let  $y_n = x_n - \hat{x}_n$ , let  $p$  be large, and let  $x_n$  be an i.i.d. random process. Describe the power spectrum of  $y_n$ . Justify your answer.

Name: \_\_\_\_\_