

**Midterm #3 of ECE301, Section 1 and Section 2**

6:30-7:30pm, Wednesday, November 12, 2014.

1. Please make sure that it is your name printed on the exam booklet. Enter your student ID number, and signature in the space provided on this page, **NOW!**
2. This is a closed book exam.
3. This exam contains multiple choice questions and work-out questions. For multiple choice questions, there is no need to justify your answers. You have one hour to complete it. The students are suggested not spending too much time on a single question, and working on those that you know how to solve.
4. Use the back of each page for rough work.
5. Neither calculators nor help sheets are allowed.

Name:

Student ID:

I certify that I have neither given nor received unauthorized aid on this exam.

Signature:

Date:

*Question 1:* [28%, Work-out question, Learning Objectives 2, 3, 4, 5]

Consider an input signal  $x(t)$  and an LTI system with impulse response  $h(t)$ . The expressions of  $x(t)$  and  $h(t)$  are:

$$x(t) = \sum_{k=-\infty}^{\infty} \delta(t - k)$$
$$h(t) = \begin{cases} e^{-j2\pi t} & \text{if } -1 < t < 1 \\ 0 & \text{otherwise} \end{cases}$$

1. [10%] Find the frequency response  $H(j\omega)$  of the LTI system and plot it for the range of  $-4\pi \leq \omega \leq 4\pi$ .
2. [8%] Find the Fourier transform  $X(j\omega)$  of the input  $x(t)$  and plot it for the range of  $-4\pi \leq \omega \leq 4\pi$ .
3. [10%] Let  $y(t)$  denote the output of the LTI system when the input is  $x(t)$ . Do (i) find the expression of  $y(t)$ ; and (ii) plot  $Y(j\omega)$  for the range of  $-4\pi \leq \omega \leq 4\pi$ .

Hint: If you do not know the answers to the first two subquestions, you can assume  $y(t) = (\cos(\pi t) + 1) + \sin(2\pi t) + 3 * (\mathcal{U}(t + 1) - \mathcal{U}(t - 1))$  and use this  $y(t)$  to answer tasks (i) and (ii). You will get 10 points if your answers are correct.



*Question 2:* [22%, Work-out question, Learning Objectives 4, 5] Consider a periodic discrete time signal  $x[n]$ , of which the period is 50. Suppose we also know that the Discrete-Time Fourier Series Coefficients  $a_k$  is

$$a_k = \begin{cases} 1 & \text{if } 1 \leq k \leq 19 \\ -1 & \text{if } 31 \leq k \leq 49 \\ 0 & \text{if } k = 0 \text{ or } 20 \leq k \leq 30 \end{cases}$$

1. [7%] What is value of  $\sum_{n=51}^{100} x[n]$ ?
2. [7%] What is the value of  $x[-25]$ ?
3. [8%] What is the average power of the signal  $x[n]$ ?



*Question 3:* [12%, Work-out question, Learning Objectives 4, 5]

Consider a discrete-time signal:

$$x[n] = \begin{cases} \cos(n) & \text{if } -10 \leq n \leq 10 \\ 0 & \text{otherwise} \end{cases}$$

1. [10%] Find the Discrete-Time Fourier Transform  $X(e^{j\omega})$  of  $x[n]$ .
2. [2%] Is your  $X(e^{j\omega})$  periodic?

Hint: You may need to use the formula  $\sum_{k=1}^K ar^{k-1} = \frac{a(1-r^K)}{1-r}$  if  $r \neq 1$ .



*Question 4:* [15%, Work-out question, Learning Objectives 3, 4, 5] Consider the following signal

$$x(t) = \frac{\sin(t) \cos(4t) \sin(2t)}{\pi^2 t^2}. \quad (1)$$

Plot the Continuous-Time Fourier transform  $X(j\omega)$  for the range of  $-8 < \omega < 8$ .

Hint: If you do not know the answer, you should write down as much as you know so that partial credit can be given.





*Question 5:* [23%, Work-out question, Learning Objective 3, 4, 5]

An AM radio station A would like to send an input signal  $x_1(t)$  over a sine carrier of frequency 920k Hz. More specifically, we denote the input signal as  $x_1(t)$  and use  $y(t)$  to denote the AM modulated signal, which will be sent out by the transmitter.

1. [2%] What is the value of the carrier frequency with the unit being (rad/sec)?
2. [2%] Write down the input/output relationship (equation) between  $x_1(t)$  and  $y(t)$ .  
Hint: Please pay attention to the requirement that the transmitter is using a sine signal as the carrier, not a cosine signal.

A nearby AM radio station B would like to send another signal  $x_2(t)$  over a sine carrier but this time the carrier frequency is 930k Hz. It turns out that when both stations A and B are transmitting simultaneously, their signals are “interfering heavily with each other”. It turns out that the reason is that both radio stations A and B forgot to low-pass filter their signals  $x_1(t)$  and  $x_2(t)$  before their transmission.

3. [5%] Explain why “not low-pass filtering it before transmission” can cause problems when both radio stations transmit simultaneously. (A very quick sentence or two will suffice).

To avoid interference, it is critical that we low-pass filter the base-band signals  $x_1(t)$  and  $x_2(t)$  before transmitting at carrier frequencies 920k and 930k Hz, respectively.

4. [8%] What is the (largest) cutoff frequency of the low-pass filter one should use to avoid the interference between radio stations A and B? Please make sure your unit is correct.
5. [6%] The receiver 1 uses synchronous demodulation to listen to radio station A. Let  $w(t)$  denote the resulting signal after demodulation. Write down the relationship between  $y(t)$  and  $w(t)$ .

Hint: Your answer should consist of statements like “multiplying .....” and/or “using a filter.....” Please be specific about the parameters of the filters. If you prefer, you can also use a block diagram (flow chart) to describe your demodulation system instead of using sentences.



Discrete-time Fourier series

$$x[n] = \sum_{k=\langle N \rangle} a_k e^{jk(2\pi/N)n} \quad (1)$$

$$a_k = \frac{1}{N} \sum_{n=\langle N \rangle} x[n] e^{-jk(2\pi/N)n} \quad (2)$$

Continuous-time Fourier series

$$x(t) = \sum_{k=-\infty}^{\infty} a_k e^{jk(2\pi/T)t} \quad (3)$$

$$a_k = \frac{1}{T} \int_T x(t) e^{-jk(2\pi/T)t} dt \quad (4)$$

Continuous-time Fourier transform

$$x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(j\omega) e^{j\omega t} d\omega \quad (5)$$

$$X(j\omega) = \int_{-\infty}^{\infty} x(t) e^{-j\omega t} dt \quad (6)$$

Discrete-time Fourier transform

$$x[n] = \frac{1}{2\pi} \int_{2\pi} X(j\omega) e^{j\omega n} d\omega \quad (7)$$

$$X(e^{j\omega}) = \sum_{n=-\infty}^{\infty} x[n] e^{-j\omega n} \quad (8)$$

Laplace transform

$$x(t) = \frac{1}{2\pi} e^{\sigma t} \int_{-\infty}^{\infty} X(\sigma + j\omega) e^{j\omega t} d\omega \quad (9)$$

$$X(s) = \int_{-\infty}^{\infty} x(t) e^{-st} dt \quad (10)$$

Z transform

$$x[n] = r^n \mathcal{F}^{-1}(X(re^{j\omega})) \quad (11)$$

$$X(z) = \sum_{n=-\infty}^{\infty} x[n] z^{-n} \quad (12)$$

TABLE 3.1 PROPERTIES OF CONTINUOUS-TIME FOURIER SERIES

Property	Section	Periodic Signal	Fourier Series Coefficients
		$x(t)$ } Periodic with period $T$ and $y(t)$ } fundamental frequency $\omega_0 = 2\pi/T$	$a_k$ $b_k$
Linearity	3.5.1	$Ax(t) + By(t)$	$Aa_k + Bb_k$
Time Shifting	3.5.2	$x(t - t_0)$	$a_k e^{-jk\omega_0 t_0} = a_k e^{-jk(2\pi/T)t_0}$
Frequency Shifting		$e^{jM\omega_0 t} x(t) = e^{jM(2\pi/T)t} x(t)$	$a_{k-M}$
Conjugation	3.5.6	$x^*(t)$	$a_{-k}^*$
Time Reversal	3.5.3	$x(-t)$	$a_{-k}$
Time Scaling	3.5.4	$x(\alpha t), \alpha > 0$ (periodic with period $T/\alpha$ )	$a_k$
Periodic Convolution		$\int_T x(\tau)y(t - \tau)d\tau$	$T a_k b_k$
Multiplication	3.5.5	$x(t)y(t)$	$\sum_{l=-\infty}^{+\infty} a_l b_{k-l}$
Differentiation		$\frac{dx(t)}{dt}$	$jk\omega_0 a_k = jk \frac{2\pi}{T} a_k$
Integration		$\int_{-\infty}^t x(t) dt$ (finite valued and periodic only if $a_0 = 0$ )	$\left(\frac{1}{jk\omega_0}\right) a_k = \left(\frac{1}{jk(2\pi/T)}\right) a_k$
Conjugate Symmetry for Real Signals	3.5.6	$x(t)$ real	$\begin{cases} a_k = a_{-k}^* \\ \Re\{a_k\} = \Re\{a_{-k}\} \\ \Im\{a_k\} = -\Im\{a_{-k}\} \\  a_k  =  a_{-k}  \\ \angle a_k = -\angle a_{-k} \end{cases}$
Real and Even Signals	3.5.6	$x(t)$ real and even	$a_k$ real and even
Real and Odd Signals	3.5.6	$x(t)$ real and odd	$a_k$ purely imaginary and odd
Even-Odd Decomposition of Real Signals		$\begin{cases} x_e(t) = \mathcal{E}\{x(t)\} & [x(t) \text{ real}] \\ x_o(t) = \mathcal{O}\{x(t)\} & [x(t) \text{ real}] \end{cases}$	$\begin{cases} \Re\{a_k\} \\ \Im\{a_k\} \end{cases}$
Parseval's Relation for Periodic Signals			
$\frac{1}{T} \int_T  x(t) ^2 dt = \sum_{k=-\infty}^{+\infty}  a_k ^2$			

three examples, we illustrate this. The last example in this section then demonstrates how properties of a signal can be used to characterize the signal in great detail.

### Example 3.6

Consider the signal  $g(t)$  with a fundamental period of 4, shown in Figure 3.10. We could determine the Fourier series representation of  $g(t)$  directly from the analysis equation (3.39). Instead, we will use the relationship of  $g(t)$  to the symmetric periodic square wave  $x(t)$  in Example 3.5. Referring to that example, we see that, with  $T = 4$  and  $T_1 = 1$ ,

$$g(t) = x(t - 1) - 1/2. \quad (3.40)$$

Thus, in general, *none* of the finite partial sums in eq. (3.52) yield the exact values of  $x(t)$ , and convergence issues, such as those considered in Section 3.4, arise as we consider the problem of evaluating the limit as the number of terms approaches infinity.

### 3.7 PROPERTIES OF DISCRETE-TIME FOURIER SERIES

There are strong similarities between the properties of discrete-time and continuous-time Fourier series. This can be readily seen by comparing the discrete-time Fourier series properties summarized in Table 3.2 with their continuous-time counterparts in Table 3.1.

**TABLE 3.2** PROPERTIES OF DISCRETE-TIME FOURIER SERIES

Property	Periodic Signal	Fourier Series Coefficients
	$x[n]$ } Periodic with period $N$ and $y[n]$ } fundamental frequency $\omega_0 = 2\pi/N$	$a_k$ } Periodic with $b_k$ } period $N$
Linearity	$Ax[n] + By[n]$	$Aa_k + Bb_k$
Time Shifting	$x[n - n_0]$	$a_k e^{-jk(2\pi/N)n_0}$
Frequency Shifting	$e^{jM(2\pi/N)n} x[n]$	$a_{k-M}$
Conjugation	$x^*[n]$	$a_{-k}^*$
Time Reversal	$x[-n]$	$a_{-k}$
Time Scaling	$x_{(m)}[n] = \begin{cases} x[n/m], & \text{if } n \text{ is a multiple of } m \\ 0, & \text{if } n \text{ is not a multiple of } m \end{cases}$ (periodic with period $mN$ )	$\frac{1}{m} a_k$ (viewed as periodic) (with period $mN$ )
Periodic Convolution	$\sum_{r=(N)} x[r]y[n-r]$	$Na_k b_k$
Multiplication	$x[n]y[n]$	$\sum_{l=(N)} a_l b_{k-l}$
First Difference	$x[n] - x[n-1]$	$(1 - e^{-jk(2\pi/N)})a_k$
Running Sum	$\sum_{k=-\infty}^n x[k]$ (finite valued and periodic only) (if $a_0 = 0$ )	$\left(\frac{1}{1 - e^{-jk(2\pi/N)}}\right)a_k$
Conjugate Symmetry for Real Signals	$x[n]$ real	$\begin{cases} a_k = a_{-k}^* \\ \Re\{a_k\} = \Re\{a_{-k}\} \\ \Im\{a_k\} = -\Im\{a_{-k}\} \\  a_k  =  a_{-k}  \\ \angle a_k = -\angle a_{-k} \end{cases}$
Real and Even Signals	$x[n]$ real and even	$a_k$ real and even
Real and Odd Signals	$x[n]$ real and odd	$a_k$ purely imaginary and odd
Even-Odd Decomposition of Real Signals	$\begin{cases} x_e[n] = \mathcal{E}\{x[n]\} & [x[n] \text{ real}] \\ x_o[n] = \mathcal{O}\{x[n]\} & [x[n] \text{ real}] \end{cases}$	$\begin{cases} \Re\{a_k\} \\ j\Im\{a_k\} \end{cases}$

Parseval's Relation for Periodic Signals

$$\frac{1}{N} \sum_{n=(N)} |x[n]|^2 = \sum_{k=(N)} |a_k|^2$$

## 4.6 TABLES OF FOURIER PROPERTIES AND OF BASIC FOURIER TRANSFORM PAIRS

In the preceding sections and in the problems at the end of the chapter, we have considered some of the important properties of the Fourier transform. These are summarized in Table 4.1, in which we have also indicated the section of this chapter in which each property has been discussed.

In Table 4.2, we have assembled a list of many of the basic and important Fourier transform pairs. We will encounter many of these repeatedly as we apply the tools of

**TABLE 4.1** PROPERTIES OF THE FOURIER TRANSFORM

Section	Property	Aperiodic signal	Fourier transform
		$x(t)$ $y(t)$	$X(j\omega)$ $Y(j\omega)$
<hr/>			
4.3.1	Linearity	$ax(t) + by(t)$	$aX(j\omega) + bY(j\omega)$
4.3.2	Time Shifting	$x(t - t_0)$	$e^{-j\omega t_0} X(j\omega)$
4.3.6	Frequency Shifting	$e^{j\omega_0 t} x(t)$	$X(j(\omega - \omega_0))$
4.3.3	Conjugation	$x^*(t)$	$X^*(-j\omega)$
4.3.5	Time Reversal	$x(-t)$	$X(-j\omega)$
4.3.5	Time and Frequency Scaling	$x(at)$	$\frac{1}{ a } X\left(\frac{j\omega}{a}\right)$
4.4	Convolution	$x(t) * y(t)$	$X(j\omega)Y(j\omega)$
4.5	Multiplication	$x(t)y(t)$	$\frac{1}{2\pi} \int_{-\infty}^{+\infty} X(j\theta)Y(j(\omega - \theta))d\theta$
4.3.4	Differentiation in Time	$\frac{d}{dt}x(t)$	$j\omega X(j\omega)$
4.3.4	Integration	$\int_{-\infty}^t x(t)dt$	$\frac{1}{j\omega} X(j\omega) + \pi X(0)\delta(\omega)$
4.3.6	Differentiation in Frequency	$tx(t)$	$j \frac{d}{d\omega} X(j\omega)$
4.3.3	Conjugate Symmetry for Real Signals	$x(t)$ real	$\begin{cases} X(j\omega) = X^*(-j\omega) \\ \Re\{X(j\omega)\} = \Re\{X(-j\omega)\} \\ \Im\{X(j\omega)\} = -\Im\{X(-j\omega)\} \\  X(j\omega)  =  X(-j\omega)  \\ \angle X(j\omega) = -\angle X(-j\omega) \end{cases}$
4.3.3	Symmetry for Real and Even Signals	$x(t)$ real and even	$X(j\omega)$ real and even
4.3.3	Symmetry for Real and Odd Signals	$x(t)$ real and odd	$X(j\omega)$ purely imaginary and odd
4.3.3	Even-Odd Decomposition for Real Signals	$x_e(t) = \mathcal{E}\{x(t)\}$ [ $x(t)$ real] $x_o(t) = \mathcal{O}\{x(t)\}$ [ $x(t)$ real]	$\Re\{X(j\omega)\}$ $j\Im\{X(j\omega)\}$
<hr/>			
4.3.7	Parseval's Relation for Aperiodic Signals		
		$\int_{-\infty}^{+\infty}  x(t) ^2 dt = \frac{1}{2\pi} \int_{-\infty}^{+\infty}  X(j\omega) ^2 d\omega$	

TABLE 4.2 BASIC FOURIER TRANSFORM PAIRS

Signal	Fourier transform	Fourier series coefficients (if periodic)
$\sum_{k=-\infty}^{+\infty} a_k e^{jk\omega_0 t}$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta(\omega - k\omega_0)$	$a_k$
$e^{j\omega_0 t}$	$2\pi \delta(\omega - \omega_0)$	$a_1 = 1$ $a_k = 0$ , otherwise
$\cos \omega_0 t$	$\pi[\delta(\omega - \omega_0) + \delta(\omega + \omega_0)]$	$a_1 = a_{-1} = \frac{1}{2}$ $a_k = 0$ , otherwise
$\sin \omega_0 t$	$\frac{\pi}{j}[\delta(\omega - \omega_0) - \delta(\omega + \omega_0)]$	$a_1 = -a_{-1} = \frac{1}{2j}$ $a_k = 0$ , otherwise
$x(t) = 1$	$2\pi \delta(\omega)$	$a_0 = 1$ , $a_k = 0$ , $k \neq 0$ (this is the Fourier series representation for any choice of $T > 0$ )
Periodic square wave		
$x(t) = \begin{cases} 1, &  t  < T_1 \\ 0, & T_1 <  t  \leq \frac{T}{2} \end{cases}$	$\sum_{k=-\infty}^{+\infty} \frac{2 \sin k\omega_0 T_1}{k} \delta(\omega - k\omega_0)$	$\frac{\omega_0 T_1}{\pi} \operatorname{sinc}\left(\frac{k\omega_0 T_1}{\pi}\right) = \frac{\sin k\omega_0 T_1}{k\pi}$
and $x(t + T) = x(t)$		
$\sum_{n=-\infty}^{+\infty} \delta(t - nT)$	$\frac{2\pi}{T} \sum_{k=-\infty}^{+\infty} \delta\left(\omega - \frac{2\pi k}{T}\right)$	$a_k = \frac{1}{T}$ for all $k$
$x(t) \begin{cases} 1, &  t  < T_1 \\ 0, &  t  > T_1 \end{cases}$	$\frac{2 \sin \omega T_1}{\omega}$	—
$\frac{\sin Wt}{\pi t}$	$X(j\omega) = \begin{cases} 1, &  \omega  < W \\ 0, &  \omega  > W \end{cases}$	—
$\delta(t)$	1	—
$u(t)$	$\frac{1}{j\omega} + \pi \delta(\omega)$	—
$\delta(t - t_0)$	$e^{-j\omega t_0}$	—
$e^{-at} u(t), \operatorname{Re}\{a\} > 0$	$\frac{1}{a + j\omega}$	—
$t e^{-at} u(t), \operatorname{Re}\{a\} > 0$	$\frac{1}{(a + j\omega)^2}$	—
$\frac{t^{n-1}}{(n-1)!} e^{-at} u(t), \operatorname{Re}\{a\} > 0$	$\frac{1}{(a + j\omega)^n}$	—



**TABLE 5.1** PROPERTIES OF THE DISCRETE-TIME FOURIER TRANSFORM

Section	Property	Aperiodic Signal	Fourier Transform
		$x[n]$	$X(e^{j\omega})$ } periodic with
		$y[n]$	$Y(e^{j\omega})$ } period $2\pi$
5.3.2	Linearity	$ax[n] + by[n]$	$aX(e^{j\omega}) + bY(e^{j\omega})$
5.3.3	Time Shifting	$x[n - n_0]$	$e^{-j\omega n_0} X(e^{j\omega})$
5.3.3	Frequency Shifting	$e^{j\omega_0 n} x[n]$	$X(e^{j(\omega - \omega_0)})$
5.3.4	Conjugation	$x^*[n]$	$X^*(e^{-j\omega})$
5.3.6	Time Reversal	$x[-n]$	$X(e^{-j\omega})$
5.3.7	Time Expansion	$x_{(k)}[n] = \begin{cases} x[n/k], & \text{if } n = \text{multiple of } k \\ 0, & \text{if } n \neq \text{multiple of } k \end{cases}$	$X(e^{jk\omega})$
5.4	Convolution	$x[n] * y[n]$	$X(e^{j\omega})Y(e^{j\omega})$
5.5	Multiplication	$x[n]y[n]$	$\frac{1}{2\pi} \int_{2\pi} X(e^{j\theta})Y(e^{j(\omega - \theta)})d\theta$
5.3.5	Differencing in Time	$x[n] - x[n - 1]$	$(1 - e^{-j\omega})X(e^{j\omega})$
5.3.5	Accumulation	$\sum_{k=-\infty}^n x[k]$	$\frac{1}{1 - e^{-j\omega}} X(e^{j\omega})$
5.3.8	Differentiation in Frequency	$nx[n]$	$j \frac{dX(e^{j\omega})}{d\omega}$
5.3.4	Conjugate Symmetry for Real Signals	$x[n]$ real	$\begin{cases} X(e^{j\omega}) = X^*(e^{-j\omega}) \\ \Re\{X(e^{j\omega})\} = \Re\{X(e^{-j\omega})\} \\ \Im\{X(e^{j\omega})\} = -\Im\{X(e^{-j\omega})\} \\  X(e^{j\omega})  =  X(e^{-j\omega})  \\ \angle X(e^{j\omega}) = -\angle X(e^{-j\omega}) \end{cases}$
5.3.4	Symmetry for Real, Even Signals	$x[n]$ real and even	$X(e^{j\omega})$ real and even
5.3.4	Symmetry for Real, Odd Signals	$x[n]$ real and odd	$X(e^{j\omega})$ purely imaginary and odd
5.3.4	Even-odd Decomposition of Real Signals	$x_e[n] = \mathcal{E}\{x[n]\}$ [ $x[n]$ real ] $x_o[n] = \mathcal{O}\{x[n]\}$ [ $x[n]$ real ]	$\Re\{X(e^{j\omega})\}$ $j\Im\{X(e^{j\omega})\}$
5.3.9	Parseval's Relation for Aperiodic Signals	$\sum_{n=-\infty}^{+\infty}  x[n] ^2 = \frac{1}{2\pi} \int_{2\pi}  X(e^{j\omega}) ^2 d\omega$	

a duality relationship between the discrete-time Fourier transform and the continuous-time Fourier series. This relation is discussed in Section 5.7.2.

### 5.7.1 Duality in the Discrete-Time Fourier Series

Since the Fourier series coefficients  $a_k$  of a periodic signal  $x[n]$  are themselves a periodic sequence, we can expand the sequence  $a_k$  in a Fourier series. The duality property for discrete-time Fourier series implies that the Fourier series coefficients for the periodic sequence  $a_k$  are the values of  $(1/N)x[-n]$  (i.e., are proportional to the values of the original

**TABLE 5.2 BASIC DISCRETE-TIME FOURIER TRANSFORM PAIRS**

Signal	Fourier Transform	Fourier Series Coefficients (if periodic)
$\sum_{k=(N)} a_k e^{jk(2n/N)n}$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$	$a_k$
$e^{j\omega_0 n}$	$2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - \omega_0 - 2\pi l)$	(a) $\omega_0 = \frac{2\pi m}{N}$ $a_k = \begin{cases} 1, & k = m, m \pm N, m \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic
$\cos \omega_0 n$	$\pi \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) + \delta(\omega + \omega_0 - 2\pi l)\}$	(a) $\omega_0 = \frac{2\pi m}{N}$ $a_k = \begin{cases} \frac{1}{2}, & k = \pm m, \pm m \pm N, \pm m \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic
$\sin \omega_0 n$	$\frac{\pi}{j} \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) - \delta(\omega + \omega_0 - 2\pi l)\}$	(a) $\omega_0 = \frac{2\pi r}{N}$ $a_k = \begin{cases} \frac{1}{2j}, & k = r, r \pm N, r \pm 2N, \dots \\ -\frac{1}{2j}, & k = -r, -r \pm N, -r \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic
$x[n] = 1$	$2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - 2\pi l)$	$a_k = \begin{cases} 1, & k = 0, \pm N, \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$
Periodic square wave $x[n] = \begin{cases} 1, &  n  \leq N_1 \\ 0, & N_1 <  n  \leq N/2 \end{cases}$ and $x[n + N] = x[n]$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$	$a_k = \frac{\sin[(2\pi k/N)(N_1 + \frac{1}{2})]}{N \sin[2\pi k/2N]}, k \neq 0, \pm N, \pm 2N, \dots$ $a_k = \frac{2N_1 + 1}{N}, k = 0, \pm N, \pm 2N, \dots$
$\sum_{k=-\infty}^{+\infty} \delta[n - kN]$	$\frac{2\pi}{N} \sum_{k=-\infty}^{+\infty} \delta\left(\omega - \frac{2\pi k}{N}\right)$	$a_k = \frac{1}{N}$ for all $k$
$a^n u[n],  a  < 1$	$\frac{1}{1 - ae^{-j\omega}}$	—
$x[n] = \begin{cases} 1, &  n  \leq N_1 \\ 0, &  n  > N_1 \end{cases}$	$\frac{\sin[\omega(N_1 + \frac{1}{2})]}{\sin(\omega/2)}$	—
$\frac{\sin Wn}{\pi n} = \frac{W}{\pi} \text{sinc}\left(\frac{Wn}{\pi}\right)$ $0 < W < \pi$	$X(\omega) = \begin{cases} 1, & 0 \leq  \omega  \leq W \\ 0, & W <  \omega  \leq \pi \end{cases}$ $X(\omega)$ periodic with period $2\pi$	—
$\delta[n]$	1	—
$u[n]$	$\frac{1}{1 - e^{-j\omega}} + \sum_{k=-\infty}^{+\infty} \pi \delta(\omega - 2\pi k)$	—
$\delta[n - n_0]$	$e^{-j\omega n_0}$	—
$(n + 1)a^n u[n],  a  < 1$	$\frac{1}{(1 - ae^{-j\omega})^2}$	—
$\frac{(n + r - 1)!}{n!(r - 1)!} a^n u[n],  a  < 1$	$\frac{1}{(1 - ae^{-j\omega})^r}$	—