

**Midterm #3 of ECE301-003, 004 (CRN 17101, 17102)**

8–9pm, Wednesday, November 13, 2019, WTHR 200.

1. Please make sure that it is your name printed on the exam booklet. Enter your student ID number, and signature in the space provided on this page, **NOW!**
2. This is a closed book exam.
3. This exam contains multiple choice questions and work-out questions. For multiple choice questions, there is no need to justify your answers. You have one hour to complete it. The students are suggested not spending too much time on a single question, and working on those that you know how to solve.
4. Use the back of each page for rough work.
5. Neither calculators nor help sheets are allowed.

Name:

Student ID:

As a Boiler Maker pursuing academic excellence, I pledge to be honest and true in all that I do. Accountable together — We are Purdue.

Signature:

Date:

*Question 1:* [14%, Work-out question, Learning Objectives 4, 5] Consider the two following discrete-time signals:

$$x[n] = \cos\left(\frac{\pi n}{4}\right) \quad (1)$$

$$y[n] = \cos\left(\frac{5\pi n + \pi}{4}\right) \quad (2)$$

1. [2%] Find the DTFS  $a_k$  of  $x[n]$ .
2. [6%] Find the DTFS  $b_k$  of  $y[n]$  and plot  $b_k$  for the range of  $k = 0$  to 10.
3. [6%] Let  $z[n] = x[n] \cdot y[n]$ . Let  $c_k$  denote the DTFS of  $z[n]$ . Find the values of  $c_2$ .

Hint: If you do not know the answers of the previous two sub-questions you can assume  $a_k = 1$  if  $0 \leq k \leq 2$  and  $a_k = 0$  if  $3 \leq k \leq 7$  and write  $c_2$  as a function of  $b_k$ . You will receive 4 points if your answer is correct.



*Question 2:* [15%, Work-out question, Learning Objectives 2, 3, 4, and 5] Consider the following continuous-time signals:

$$x(t) = \frac{\sin(3t)}{2t} \quad (3)$$

$$y(t) = \frac{\sin(2t)}{4t} \quad (4)$$

$$z(t) = (x(t) \cdot y(t)) * x(t). \quad (5)$$

Find the CTFT  $Z(j\omega)$  of  $z(t)$ .



*Question 3:* [10%, Work-out question, Learning Objectives 4 and 5] Consider a continuous-time LTI system governed by the following differential equation:

$$\frac{d^2y(t)}{dt^2} + 3\frac{dy(t)}{dt} + 2y(t) = 2\frac{dx(t)}{dt} + 3x(t) \quad (6)$$

1. [10%] Find the expression of  $y(t)$  when the input is  $x(t) = \sum_{k=5}^7 e^{j(k^2-k)t}$ .



*Question 4:* [20%, Work-out question, Learning Objectives 2, 3, 4 and 5] Consider the following DT signal  $x[n] = e^{j3(n-100)} \cdot 2^{-n+100}U[n - 100]$ .

1. [8%] Find the expression of  $X(e^{j\omega})$ .
2. [6%] Find the value of  $\int_{\pi}^{3\pi} X(e^{j\omega})d\omega$ .
3. [6%] Find the value of  $\int_0^{10\pi} |X(e^{j\omega})|^2 d\omega$ .

Hint: The following formula may be useful: If  $|r| < 1$ , then

$$\sum_{k=1}^{\infty} ar^{k-1} = \frac{a}{1-r}. \quad (7)$$





*Question 5:* [18%, Work-out question, Learning Objectives 4, 5, and 6] Consider a discrete time signal

$$x[n] = \sin(1.25\pi n) + 2e^{j2.5\pi n} \quad (8)$$

Plot the corresponding DTFT  $X(e^{j\omega})$  for the range of  $-2\pi < \omega < 2\pi$ .

Hint: There is no need to write down the expression of  $X(e^{j\omega})$ . A plot is sufficient.



*Question 6:* [23%, Learning Objectives 3, 4, 5, and 6] Consider the following *frequency scrambler* system. The input signal is  $x(t) = \cos(2\pi t)$ . We first multiply  $x(t)$  by  $\cos(10\pi t)$ . That is,

$$y(t) = x(t) \cdot \cos(10\pi t).$$

We then pass  $y(t)$  through a low pass filter with cutoff frequency 5Hz. Denote the final output by  $z(t)$ .

1. [4%] Find out the expression of the impulse response  $h(t)$  for the low pass filter with cutoff frequency 5Hz.
2. [8%] Use the CTFT to carefully analyze the system and find the expression of  $z(t)$ . Please carefully write down how the frequency spectrums  $X(j\omega)$ ,  $Y(j\omega)$  and  $Z(j\omega)$  evolve.
3. [11%] For the *descrambler*, a student figured out that all he/she needs to do is to multiple  $z(t)$  by  $\cos(10\pi t)$  again to get  $w(t) = z(t) \cdot \cos(10\pi t)$  and then pass  $w(t)$  through a low pass filter with cutoff frequency 5Hz. Denote the final output by  $\hat{x}(t)$ . However, when he/she played the descrambled signal  $\hat{x}(t)$ , he/she realized that  $\hat{x}(t)$  is not identical to the original signal  $x(t)$  anymore. Please (i) [7%] carefully analyze the descrambler in the frequency domain; (ii) [2%] Describe how  $\hat{x}(t)$  sounds when compared to the original signal  $x(t)$ ; and (iii) [2%] Describe how you will fix the descrambler so that  $\hat{x}_{\text{new}}(t) = x(t)$ .

Hint: If you do not know how to solve this question, you can write down the transmitter and receiver diagrams of AM-DSB when (i) filtering a radio signal to make it of bandwidth 7.5k Hz; (ii) then sending the filtered signal using carrier frequency 890kHz; and (iii) the receiver needs to demodulate the original signal. You need to carefully mark all the frequency parameters used in your scheme with the correct unit. If your answer is correct, you will receive 11 points.



Discrete-time Fourier series

$$x[n] = \sum_{k=\langle N \rangle} a_k e^{jk(2\pi/N)n} \quad (1)$$

$$a_k = \frac{1}{N} \sum_{n=\langle N \rangle} x[n] e^{-jk(2\pi/N)n} \quad (2)$$

Continuous-time Fourier series

$$x(t) = \sum_{k=-\infty}^{\infty} a_k e^{jk(2\pi/T)t} \quad (3)$$

$$a_k = \frac{1}{T} \int_T x(t) e^{-jk(2\pi/T)t} dt \quad (4)$$

Continuous-time Fourier transform

$$x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(j\omega) e^{j\omega t} d\omega \quad (5)$$

$$X(j\omega) = \int_{-\infty}^{\infty} x(t) e^{-j\omega t} dt \quad (6)$$

Discrete-time Fourier transform

$$x[n] = \frac{1}{2\pi} \int_{2\pi} X(e^{j\omega}) e^{j\omega n} d\omega \quad (7)$$

$$X(e^{j\omega}) = \sum_{n=-\infty}^{\infty} x[n] e^{-j\omega n} \quad (8)$$

Laplace transform

$$x(t) = \frac{1}{2\pi} e^{\sigma t} \int_{-\infty}^{\infty} X(\sigma + j\omega) e^{j\omega t} d\omega \quad (9)$$

$$X(s) = \int_{-\infty}^{\infty} x(t) e^{-st} dt \quad (10)$$

Z transform

$$x[n] = r^n \mathcal{F}^{-1}(X(re^{j\omega})) \quad (11)$$

$$X(z) = \sum_{n=-\infty}^{\infty} x[n] z^{-n} \quad (12)$$

TABLE 3.1 PROPERTIES OF CONTINUOUS-TIME FOURIER SERIES

| Property  | Section | Periodic Signal  | Fourier Series Coefficients  |
|---|---------|--|--|
|   |         | $x(t)$ } Periodic with period $T$ and<br>$y(t)$ } fundamental frequency $\omega_0 = 2\pi/T$  | $a_k$<br>$b_k$   |
| Linearity   | 3.5.1   | $Ax(t) + By(t)$  | $Aa_k + Bb_k$  |
| Time Shifting   | 3.5.2   | $x(t - t_0)$   | $a_k e^{-jk\omega_0 t_0} = a_k e^{-jk(2\pi/T)t_0}$   |
| Frequency Shifting  |         | $e^{jM\omega_0 t} x(t) = e^{jM(2\pi/T)t} x(t)$   | $a_{k-M}$  |
| Conjugation   | 3.5.6   | $x^*(t)$   | $a_{-k}^*$   |
| Time Reversal   | 3.5.3   | $x(-t)$  | $a_{-k}$   |
| Time Scaling  | 3.5.4   | $x(\alpha t), \alpha > 0$ (periodic with period $T/\alpha$ )   | $a_k$  |
| Periodic Convolution  |         | $\int_T x(\tau)y(t - \tau)d\tau$   | $T a_k b_k$  |
| Multiplication  | 3.5.5   | $x(t)y(t)$   | $\sum_{l=-\infty}^{+\infty} a_l b_{k-l}$   |
| Differentiation   |         | $\frac{dx(t)}{dt}$   | $jk\omega_0 a_k = jk \frac{2\pi}{T} a_k$   |
| Integration   |         | $\int_{-\infty}^t x(t) dt$ (finite valued and periodic only if $a_0 = 0$ )   | $\left(\frac{1}{jk\omega_0}\right) a_k = \left(\frac{1}{jk(2\pi/T)}\right) a_k$  |
| Conjugate Symmetry for Real Signals                                   | 3.5.6   | $x(t)$ real  | $\begin{cases} a_k = a_{-k}^* \\ \Re\{a_k\} = \Re\{a_{-k}\} \\ \Im\{a_k\} = -\Im\{a_{-k}\} \\  a_k  =  a_{-k}  \\ \angle a_k = -\angle a_{-k} \end{cases}$ |
| Real and Even Signals   | 3.5.6   | $x(t)$ real and even   | $a_k$ real and even  |
| Real and Odd Signals  | 3.5.6   | $x(t)$ real and odd  | $a_k$ purely imaginary and odd   |
| Even-Odd Decomposition of Real Signals                                |         | $\begin{cases} x_e(t) = \mathcal{E}\{x(t)\} & [x(t) \text{ real}] \\ x_o(t) = \mathcal{O}\{x(t)\} & [x(t) \text{ real}] \end{cases}$ | $\begin{cases} \Re\{a_k\} \\ \Im\{a_k\} \end{cases}$   |
| Parseval's Relation for Periodic Signals                              |         |  |  |
| $\frac{1}{T} \int_T  x(t) ^2 dt = \sum_{k=-\infty}^{+\infty}  a_k ^2$ |         |  |  |

three examples, we illustrate this. The last example in this section then demonstrates how properties of a signal can be used to characterize the signal in great detail.

### Example 3.6

Consider the signal  $g(t)$  with a fundamental period of 4, shown in Figure 3.10. We could determine the Fourier series representation of  $g(t)$  directly from the analysis equation (3.39). Instead, we will use the relationship of  $g(t)$  to the symmetric periodic square wave  $x(t)$  in Example 3.5. Referring to that example, we see that, with  $T = 4$  and  $T_1 = 1$ ,

$$g(t) = x(t - 1) - 1/2. \quad (3.40)$$

Thus, in general, *none* of the finite partial sums in eq. (3.52) yield the exact values of  $x(t)$ , and convergence issues, such as those considered in Section 3.4, arise as we consider the problem of evaluating the limit as the number of terms approaches infinity.

### 3.7 PROPERTIES OF DISCRETE-TIME FOURIER SERIES

There are strong similarities between the properties of discrete-time and continuous-time Fourier series. This can be readily seen by comparing the discrete-time Fourier series properties summarized in Table 3.2 with their continuous-time counterparts in Table 3.1.

**TABLE 3.2** PROPERTIES OF DISCRETE-TIME FOURIER SERIES

| Property   | Periodic Signal  | Fourier Series Coefficients  |
|--|--|--|
|  | $x[n]$ } Periodic with period $N$ and<br>$y[n]$ } fundamental frequency $\omega_0 = 2\pi/N$  | $a_k$ } Periodic with<br>$b_k$ } period $N$  |
| Linearity  | $Ax[n] + By[n]$  | $Aa_k + Bb_k$  |
| Time Shifting  | $x[n - n_0]$   | $a_k e^{-jk(2\pi/N)n_0}$   |
| Frequency Shifting   | $e^{jM(2\pi/N)n} x[n]$   | $a_{k-M}$  |
| Conjugation  | $x^*[n]$   | $a_{-k}^*$   |
| Time Reversal  | $x[-n]$  | $a_{-k}$   |
| Time Scaling   | $x_{(m)}[n] = \begin{cases} x[n/m], & \text{if } n \text{ is a multiple of } m \\ 0, & \text{if } n \text{ is not a multiple of } m \end{cases}$<br>(periodic with period $mN$ ) | $\frac{1}{m} a_k$ (viewed as periodic)<br>(with period $mN$ )  |
| Periodic Convolution                                       | $\sum_{r=(N)} x[r]y[n-r]$  | $Na_k b_k$   |
| Multiplication   | $x[n]y[n]$   | $\sum_{l=(N)} a_l b_{k-l}$   |
| First Difference   | $x[n] - x[n-1]$  | $(1 - e^{-jk(2\pi/N)})a_k$   |
| Running Sum  | $\sum_{k=-\infty}^n x[k]$ (finite valued and periodic only)<br>(if $a_0 = 0$ )   | $\left(\frac{1}{1 - e^{-jk(2\pi/N)}}\right)a_k$  |
| Conjugate Symmetry for Real Signals                        | $x[n]$ real  | $\begin{cases} a_k = a_{-k}^* \\ \Re\{a_k\} = \Re\{a_{-k}\} \\ \Im\{a_k\} = -\Im\{a_{-k}\} \\  a_k  =  a_{-k}  \\ \angle a_k = -\angle a_{-k} \end{cases}$ |
| Real and Even Signals                                      | $x[n]$ real and even   | $a_k$ real and even  |
| Real and Odd Signals                                       | $x[n]$ real and odd  | $a_k$ purely imaginary and odd   |
| Even-Odd Decomposition of Real Signals                     | $\begin{cases} x_e[n] = \mathcal{E}\{x[n]\} & [x[n] \text{ real}] \\ x_o[n] = \mathcal{O}\{x[n]\} & [x[n] \text{ real}] \end{cases}$   | $\begin{cases} \Re\{a_k\} \\ j\Im\{a_k\} \end{cases}$  |
| Parseval's Relation for Periodic Signals                   |  |  |
| $\frac{1}{N} \sum_{n=(N)}  x[n] ^2 = \sum_{k=(N)}  a_k ^2$ |  |  |



## 4.6 TABLES OF FOURIER PROPERTIES AND OF BASIC FOURIER TRANSFORM PAIRS

In the preceding sections and in the problems at the end of the chapter, we have considered some of the important properties of the Fourier transform. These are summarized in Table 4.1, in which we have also indicated the section of this chapter in which each property has been discussed.

In Table 4.2, we have assembled a list of many of the basic and important Fourier transform pairs. We will encounter many of these repeatedly as we apply the tools of

**TABLE 4.1** PROPERTIES OF THE FOURIER TRANSFORM

| Section | Property                                  | Aperiodic signal  | Fourier transform  |
|---------|---|---|--|
|         |   | $x(t)$<br>$y(t)$  | $X(j\omega)$<br>$Y(j\omega)$   |
| -----   |   |   |  |
| 4.3.1   | Linearity                                 | $ax(t) + by(t)$   | $aX(j\omega) + bY(j\omega)$  |
| 4.3.2   | Time Shifting                             | $x(t - t_0)$  | $e^{-j\omega t_0} X(j\omega)$  |
| 4.3.6   | Frequency Shifting                        | $e^{j\omega_0 t} x(t)$  | $X(j(\omega - \omega_0))$  |
| 4.3.3   | Conjugation                               | $x^*(t)$  | $X^*(-j\omega)$  |
| 4.3.5   | Time Reversal                             | $x(-t)$   | $X(-j\omega)$  |
| 4.3.5   | Time and Frequency Scaling                | $x(at)$   | $\frac{1}{ a } X\left(\frac{j\omega}{a}\right)$  |
| 4.4     | Convolution                               | $x(t) * y(t)$   | $X(j\omega)Y(j\omega)$   |
| 4.5     | Multiplication                            | $x(t)y(t)$  | $\frac{1}{2\pi} \int_{-\infty}^{+\infty} X(j\theta)Y(j(\omega - \theta))d\theta$   |
| 4.3.4   | Differentiation in Time                   | $\frac{d}{dt}x(t)$  | $j\omega X(j\omega)$   |
| 4.3.4   | Integration                               | $\int_{-\infty}^t x(t)dt$   | $\frac{1}{j\omega} X(j\omega) + \pi X(0)\delta(\omega)$  |
| 4.3.6   | Differentiation in Frequency              | $tx(t)$   | $j \frac{d}{d\omega} X(j\omega)$   |
| 4.3.3   | Conjugate Symmetry for Real Signals       | $x(t)$ real   | $\begin{cases} X(j\omega) = X^*(-j\omega) \\ \Re\{X(j\omega)\} = \Re\{X(-j\omega)\} \\ \Im\{X(j\omega)\} = -\Im\{X(-j\omega)\} \\  X(j\omega)  =  X(-j\omega)  \\ \angle X(j\omega) = -\angle X(-j\omega) \end{cases}$ |
| 4.3.3   | Symmetry for Real and Even Signals        | $x(t)$ real and even  | $X(j\omega)$ real and even   |
| 4.3.3   | Symmetry for Real and Odd Signals         | $x(t)$ real and odd   | $X(j\omega)$ purely imaginary and odd  |
| 4.3.3   | Even-Odd Decomposition for Real Signals   | $x_e(t) = \mathcal{E}\{x(t)\}$ [ $x(t)$ real]<br>$x_o(t) = \mathcal{O}\{x(t)\}$ [ $x(t)$ real]          | $\Re\{X(j\omega)\}$<br>$j\Im\{X(j\omega)\}$  |
| -----   |   |   |  |
| 4.3.7   | Parseval's Relation for Aperiodic Signals |   |  |
|         |   | $\int_{-\infty}^{+\infty}  x(t) ^2 dt = \frac{1}{2\pi} \int_{-\infty}^{+\infty}  X(j\omega) ^2 d\omega$ |  |

TABLE 4.2 BASIC FOURIER TRANSFORM PAIRS

| Signal   | Fourier transform  | Fourier series coefficients<br>(if periodic)   |
|--|--|--|
| $\sum_{k=-\infty}^{+\infty} a_k e^{jk\omega_0 t}$                                    | $2\pi \sum_{k=-\infty}^{+\infty} a_k \delta(\omega - k\omega_0)$                         | $a_k$  |
| $e^{j\omega_0 t}$  | $2\pi \delta(\omega - \omega_0)$   | $a_1 = 1$<br>$a_k = 0$ , otherwise   |
| $\cos \omega_0 t$  | $\pi[\delta(\omega - \omega_0) + \delta(\omega + \omega_0)]$                             | $a_1 = a_{-1} = \frac{1}{2}$<br>$a_k = 0$ , otherwise  |
| $\sin \omega_0 t$  | $\frac{\pi}{j}[\delta(\omega - \omega_0) - \delta(\omega + \omega_0)]$                   | $a_1 = -a_{-1} = \frac{1}{2j}$<br>$a_k = 0$ , otherwise  |
| $x(t) = 1$   | $2\pi \delta(\omega)$  | $a_0 = 1$ , $a_k = 0$ , $k \neq 0$<br>(this is the Fourier series representation for any choice of $T > 0$ )           |
| Periodic square wave   |  |  |
| $x(t) = \begin{cases} 1, &  t  < T_1 \\ 0, & T_1 <  t  \leq \frac{T}{2} \end{cases}$ | $\sum_{k=-\infty}^{+\infty} \frac{2 \sin k\omega_0 T_1}{k} \delta(\omega - k\omega_0)$   | $\frac{\omega_0 T_1}{\pi} \operatorname{sinc}\left(\frac{k\omega_0 T_1}{\pi}\right) = \frac{\sin k\omega_0 T_1}{k\pi}$ |
| and<br>$x(t + T) = x(t)$   |  |  |
| $\sum_{n=-\infty}^{+\infty} \delta(t - nT)$  | $\frac{2\pi}{T} \sum_{k=-\infty}^{+\infty} \delta\left(\omega - \frac{2\pi k}{T}\right)$ | $a_k = \frac{1}{T}$ for all $k$  |
| $x(t) \begin{cases} 1, &  t  < T_1 \\ 0, &  t  > T_1 \end{cases}$                    | $\frac{2 \sin \omega T_1}{\omega}$   | —  |
| $\frac{\sin Wt}{\pi t}$  | $X(j\omega) = \begin{cases} 1, &  \omega  < W \\ 0, &  \omega  > W \end{cases}$          | —  |
| $\delta(t)$  | 1  | —  |
| $u(t)$   | $\frac{1}{j\omega} + \pi \delta(\omega)$   | —  |
| $\delta(t - t_0)$  | $e^{-j\omega t_0}$   | —  |
| $e^{-at} u(t), \operatorname{Re}\{a\} > 0$   | $\frac{1}{a + j\omega}$  | —  |
| $t e^{-at} u(t), \operatorname{Re}\{a\} > 0$   | $\frac{1}{(a + j\omega)^2}$  | —  |
| $\frac{t^{n-1}}{(n-1)!} e^{-at} u(t), \operatorname{Re}\{a\} > 0$                    | $\frac{1}{(a + j\omega)^n}$  | —  |

ansform Chap. 4

FORM PAIRS

; we have consid-  
re summarized in  
which each prop-

important Fourier  
apply the tools of

transform

( $\omega$ )

( $\theta - \theta$ ) $d\theta$

(0) $\delta(\omega)$

( $j\omega$ )

$\operatorname{Re}\{X(-j\omega)\}$

$-\operatorname{Im}\{X(-j\omega)\}$

( $j\omega$ )

$X(-j\omega)$

ven

imaginary and odd

**TABLE 5.1** PROPERTIES OF THE DISCRETE-TIME FOURIER TRANSFORM

| Section | Property                                  | Aperiodic Signal  | Fourier Transform  |
|---------|---|---|--|
|         |   | $x[n]$  | $X(e^{j\omega})$ } periodic with   |
|         |   | $y[n]$  | $Y(e^{j\omega})$ } period $2\pi$   |
| 5.3.2   | Linearity                                 | $ax[n] + by[n]$   | $aX(e^{j\omega}) + bY(e^{j\omega})$  |
| 5.3.3   | Time Shifting                             | $x[n - n_0]$  | $e^{-j\omega n_0} X(e^{j\omega})$  |
| 5.3.3   | Frequency Shifting                        | $e^{j\omega_0 n} x[n]$  | $X(e^{j(\omega - \omega_0)})$  |
| 5.3.4   | Conjugation                               | $x^*[n]$  | $X^*(e^{-j\omega})$  |
| 5.3.6   | Time Reversal                             | $x[-n]$   | $X(e^{-j\omega})$  |
| 5.3.7   | Time Expansion                            | $x_{(k)}[n] = \begin{cases} x[n/k], & \text{if } n = \text{multiple of } k \\ 0, & \text{if } n \neq \text{multiple of } k \end{cases}$ | $X(e^{jk\omega})$  |
| 5.4     | Convolution                               | $x[n] * y[n]$   | $X(e^{j\omega})Y(e^{j\omega})$   |
| 5.5     | Multiplication                            | $x[n]y[n]$  | $\frac{1}{2\pi} \int_{2\pi} X(e^{j\theta})Y(e^{j(\omega - \theta)})d\theta$  |
| 5.3.5   | Differencing in Time                      | $x[n] - x[n - 1]$   | $(1 - e^{-j\omega})X(e^{j\omega})$   |
| 5.3.5   | Accumulation                              | $\sum_{k=-\infty}^n x[k]$   | $\frac{1}{1 - e^{-j\omega}} X(e^{j\omega})$  |
| 5.3.8   | Differentiation in Frequency              | $nx[n]$   | $j \frac{dX(e^{j\omega})}{d\omega}$  |
| 5.3.4   | Conjugate Symmetry for Real Signals       | $x[n]$ real   | $\begin{cases} X(e^{j\omega}) = X^*(e^{-j\omega}) \\ \Re\{X(e^{j\omega})\} = \Re\{X(e^{-j\omega})\} \\ \Im\{X(e^{j\omega})\} = -\Im\{X(e^{-j\omega})\} \\  X(e^{j\omega})  =  X(e^{-j\omega})  \\ \angle X(e^{j\omega}) = -\angle X(e^{-j\omega}) \end{cases}$ |
| 5.3.4   | Symmetry for Real, Even Signals           | $x[n]$ real and even  | $X(e^{j\omega})$ real and even   |
| 5.3.4   | Symmetry for Real, Odd Signals            | $x[n]$ real and odd   | $X(e^{j\omega})$ purely imaginary and odd  |
| 5.3.4   | Even-odd Decomposition of Real Signals    | $x_e[n] = \mathcal{E}\{x[n]\}$ [ $x[n]$ real ]<br>$x_o[n] = \mathcal{O}\{x[n]\}$ [ $x[n]$ real ]  | $\Re\{X(e^{j\omega})\}$<br>$j\Im\{X(e^{j\omega})\}$  |
| 5.3.9   | Parseval's Relation for Aperiodic Signals | $\sum_{n=-\infty}^{+\infty}  x[n] ^2 = \frac{1}{2\pi} \int_{2\pi}  X(e^{j\omega}) ^2 d\omega$   |  |

a duality relationship between the discrete-time Fourier transform and the continuous-time Fourier series. This relation is discussed in Section 5.7.2.

### 5.7.1 Duality in the Discrete-Time Fourier Series

Since the Fourier series coefficients  $a_k$  of a periodic signal  $x[n]$  are themselves a periodic sequence, we can expand the sequence  $a_k$  in a Fourier series. The duality property for discrete-time Fourier series implies that the Fourier series coefficients for the periodic sequence  $a_k$  are the values of  $(1/N)x[-n]$  (i.e., are proportional to the values of the original

**TABLE 5.2 BASIC DISCRETE-TIME FOURIER TRANSFORM PAIRS**

| Signal  | Fourier Transform  | Fourier Series Coefficients (if periodic)  |
|---|--|--|
| $\sum_{k=(N)} a_k e^{jk(2n/N)n}$  | $2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$   | $a_k$  |
| $e^{j\omega_0 n}$   | $2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - \omega_0 - 2\pi l)$   | (a) $\omega_0 = \frac{2\pi m}{N}$<br>$a_k = \begin{cases} 1, & k = m, m \pm N, m \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$<br>(b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic   |
| $\cos \omega_0 n$   | $\pi \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) + \delta(\omega + \omega_0 - 2\pi l)\}$                                 | (a) $\omega_0 = \frac{2\pi m}{N}$<br>$a_k = \begin{cases} \frac{1}{2}, & k = \pm m, \pm m \pm N, \pm m \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$<br>(b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic   |
| $\sin \omega_0 n$   | $\frac{\pi}{j} \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) - \delta(\omega + \omega_0 - 2\pi l)\}$                       | (a) $\omega_0 = \frac{2\pi r}{N}$<br>$a_k = \begin{cases} \frac{1}{2j}, & k = r, r \pm N, r \pm 2N, \dots \\ -\frac{1}{2j}, & k = -r, -r \pm N, -r \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$<br>(b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic |
| $x[n] = 1$  | $2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - 2\pi l)$  | $a_k = \begin{cases} 1, & k = 0, \pm N, \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$  |
| Periodic square wave<br>$x[n] = \begin{cases} 1, &  n  \leq N_1 \\ 0, & N_1 <  n  \leq N/2 \end{cases}$<br>and<br>$x[n + N] = x[n]$ | $2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$   | $a_k = \frac{\sin[(2\pi k/N)(N_1 + \frac{1}{2})]}{N \sin[2\pi k/2N]}$ , $k \neq 0, \pm N, \pm 2N, \dots$<br>$a_k = \frac{2N_1 + 1}{N}$ , $k = 0, \pm N, \pm 2N, \dots$   |
| $\sum_{k=-\infty}^{+\infty} \delta[n - kN]$   | $\frac{2\pi}{N} \sum_{k=-\infty}^{+\infty} \delta\left(\omega - \frac{2\pi k}{N}\right)$   | $a_k = \frac{1}{N}$ for all $k$  |
| $a^n u[n]$ , $ a  < 1$  | $\frac{1}{1 - ae^{-j\omega}}$  | —  |
| $x[n] = \begin{cases} 1, &  n  \leq N_1 \\ 0, &  n  > N_1 \end{cases}$  | $\frac{\sin[\omega(N_1 + \frac{1}{2})]}{\sin(\omega/2)}$   | —  |
| $\frac{\sin Wn}{\pi n} = \frac{W}{\pi} \text{sinc}\left(\frac{Wn}{\pi}\right)$<br>$0 < W < \pi$                                     | $X(\omega) = \begin{cases} 1, & 0 \leq  \omega  \leq W \\ 0, & W <  \omega  \leq \pi \end{cases}$<br>$X(\omega)$ periodic with period $2\pi$ | —  |
| $\delta[n]$   | 1  | —  |
| $u[n]$  | $\frac{1}{1 - e^{-j\omega}} + \sum_{k=-\infty}^{+\infty} \pi \delta(\omega - 2\pi k)$  | —  |
| $\delta[n - n_0]$   | $e^{-j\omega n_0}$   | —  |
| $(n + 1)a^n u[n]$ , $ a  < 1$   | $\frac{1}{(1 - ae^{-j\omega})^2}$  | —  |
| $\frac{(n + r - 1)!}{n!(r - 1)!} a^n u[n]$ , $ a  < 1$  | $\frac{1}{(1 - ae^{-j\omega})^r}$  | —  |