

ECE 438 Essential Definitions and Relations

CT Metrics

1. Energy $E_x = \int_{-\infty}^{\infty} |x(t)|^2 dt$

2. Power $P_x = \lim_{T \rightarrow \infty} \frac{1}{T} \int_{-T/2}^{T/2} |x(t)|^2 dt$

3. root mean squared value $x_{rms} = \sqrt{P_x}$

4. Area $A_x = \int_{-\infty}^{\infty} x(t) dt$

5. Average value $x_{avg} = \lim_{T \rightarrow \infty} \frac{1}{T} \int_{-T/2}^{T/2} x(t) dt$

6. Magnitude $M_x = \max_{-\infty < t < \infty} |x(t)|$

DT Metrics

1. Energy $E_x = \sum_{n=-\infty}^{\infty} |x[n]|^2$

2. Power $P_x = \lim_{N \rightarrow \infty} \frac{1}{2N+1} \sum_{n=-N}^N |x[n]|^2$

3. root mean squared value $x_{rms} = \sqrt{P_x}$

4. Area $A_x = \sum_{n=-\infty}^{\infty} x[n]$

5. Average $x_{avg} = \lim_{N \rightarrow \infty} \frac{1}{2N+1} \sum_{n=-N}^N x[n]$

6. Magnitude $M_x = \max_{-\infty < n < \infty} |x[n]|$

CT Signals and Operators

1. $\text{rect}(t) = \begin{cases} 1, & |t| < 1/2 \\ 0, & |t| > 1/2 \end{cases}$

2. $\text{sinc}(t) = \frac{\sin(\pi t)}{\pi t}$

3. $\delta(t) = \lim_{\Delta \rightarrow 0} \frac{1}{\Delta} \text{rect}\left(\frac{t}{\Delta}\right)$

4. $x(t) * y(t) = \int_{-\infty}^{\infty} x(t-\tau)y(\tau) d\tau$

5. $\text{rep}_T[x(t)] = \sum_{k=-\infty}^{\infty} x(t-kT)$

6. $\text{comb}_T[x(t)] = \sum_{k=-\infty}^{\infty} x(kT)\delta(t-kT)$

Properties of the CT Impulse

1. $\int_{-\infty}^{\infty} \delta(t) dt = 1$ and $\delta(t) = 0, t \neq 0$

2. $\int_{-\infty}^{\infty} \delta(t-t_0) x(t) dt = x(t_0),$

provided $x(t)$ is continuous at $t = t_0$

3. $x(t)\delta(t-t_0) \equiv x(t_0)\delta(t-t_0)$

4. $\delta(t-t_0) * x(t) = x(t-t_0)$

5. $\delta(at-t_0) \equiv \frac{1}{|a|} \delta(t-t_0/a)$

CTFT

Sufficient conditions for existence

$$\int_{-\infty}^{\infty} |x(t)| dt < \infty \quad \text{or} \quad \int_{-\infty}^{\infty} |x(t)|^2 dt < \infty$$

Forward transform

$$X(f) = \int_{-\infty}^{\infty} x(t) e^{-j2\pi f t} dt$$

Inverse transform

$$x(t) = \int_{-\infty}^{\infty} X(f) e^{j2\pi f t} df$$

Transform Relations

1. Linearity

$$a_1 x_1(t) + a_2 x_2(t) \xleftrightarrow{\text{CTFT}} a_1 X_1(f) + a_2 X_2(f)$$

2. Scaling and shifting

$$x\left(\frac{t-t_0}{a}\right) \xleftrightarrow{\text{CTFT}} |a| X(af) e^{-j2\pi f t_0}$$

3. Modulation

$$x(t) e^{j2\pi f_0 t} \xleftrightarrow{\text{CTFT}} X(f - f_0)$$

4. Reciprocity

$$X(t) \xleftrightarrow{\text{CTFT}} x(-f)$$

5. Parseval

$$\int_{-\infty}^{\infty} |x(t)|^2 dt = \int_{-\infty}^{\infty} |X(f)|^2 df$$

6. Initial Value

$$X(0) = \int_{-\infty}^{\infty} x(t) dt$$

$$x(0) = \int_{-\infty}^{\infty} X(f) df$$

7. Convolution

$$x(t) * y(t) \xleftrightarrow{\text{CTFT}} X(f) Y(f)$$

8. Product

$$x(t) y(t) \xleftrightarrow{\text{CTFT}} X(f) * Y(f)$$

9. Transform of periodic signal

$$\text{rep}_T[x(t)] \xleftrightarrow{\text{CTFT}} \frac{1}{T} \text{comb}_{\frac{1}{T}}[X(f)]$$

10. Transform of sampled signal

$$\text{comb}_T[x(t)] \xleftrightarrow{\text{CTFT}} \frac{1}{T} \text{rep}_{\frac{1}{T}}[X(f)]$$

Transform Pairs

$$1. \text{rect}(t) \xleftrightarrow{\text{CTFT}} \text{sinc}(f)$$

$$2. \delta(t) \xleftrightarrow{\text{CTFT}} 1 \text{ and } 1 \xleftrightarrow{\text{CTFT}} \delta(f)$$

$$3. e^{j2\pi f_0 t} \xleftrightarrow{\text{CTFT}} \delta(f - f_0)$$

$$4. \cos(2\pi f_0 t) \xleftrightarrow{\text{CTFT}} \frac{1}{2} \{ \delta(f - f_0) + \delta(f + f_0) \}$$

DT Signals and Operators

$$1. u[n] = \begin{cases} 1, & n \geq 0 \\ 0, & n < 0 \end{cases}$$

$$2. \delta[n] = \begin{cases} 1, & n = 0 \\ 0, & n \neq 0 \end{cases}$$

$$3. x[n] * y[n] = \sum_{k=-\infty}^{\infty} x[n-k] y[k]$$

$$4. \text{Downsampling} \quad \begin{array}{c} x[n] \rightarrow \text{D} \downarrow \rightarrow y[n] \\ y[n] = x[Dn] \end{array}$$

$$5. \text{Upsampling} \quad \begin{array}{c} x[n] \rightarrow \text{D} \uparrow \rightarrow y[n] \\ y[n] = \begin{cases} x[n/D], & n/D \text{ integer-valued} \\ 0, & \text{else} \end{cases} \end{array}$$

Properties of the DT Impulse

$$1. \sum_{n=-\infty}^{\infty} \delta[n] = 1 \text{ and } \delta[n] = 0, n \neq 0$$

$$2. \sum_{n=-\infty}^{\infty} \delta[n - n_0] x[n] = x[n_0]$$

$$3. \delta[n - n_0] * x[n] = x[n - n_0]$$

DTFT

Sufficient conditions for existence

$$\sum_{n=-\infty}^{\infty} |x[n]| < \infty \quad \text{or} \quad \sum_{n=-\infty}^{\infty} |x[n]|^2 < \infty$$

Forward transform

$$X(\omega) = \sum_{n=-\infty}^{\infty} x[n] e^{-j\omega n}$$

Inverse transform

$$x[n] = \frac{1}{2\pi} \int_{-\pi}^{\pi} X(\omega) e^{j\omega n} d\omega$$

Transform Relations

1. Linearity

$$a_1 x_1[n] + a_2 x_2[n] \xleftrightarrow{\text{DTFT}} a_1 X_1(\omega) + a_2 X_2(\omega)$$

2. Shifting

$$x[n - n_0] \xleftrightarrow{\text{DTFT}} X(\omega) e^{-j\omega n_0}$$

3. Modulation

$$x[n] e^{j\omega_0 n} \xleftrightarrow{\text{DTFT}} X(\omega - \omega_0)$$

4. Parseval

$$\sum_{n=-\infty}^{\infty} |x[n]|^2 = \frac{1}{2\pi} \int_{-\pi}^{\pi} |X(\omega)|^2 d\omega$$

5. Initial Value

$$X(0) = \sum_{n=-\infty}^{\infty} x[n]$$


$$x[0] = \frac{1}{2\pi} \int_{-\pi}^{\pi} X(\omega) d\omega$$

6. Convolution


$$x[n] * y[n] \xleftrightarrow{\text{DTFT}} X(\omega) Y(\omega)$$

7. Product

$$x[n] y[n] \xleftrightarrow{\text{DTFT}} \frac{1}{2\pi} \int_{-\pi}^{\pi} X(\omega - \mu) Y(\mu) d\mu$$

8. Downsampling 

$$Y(\omega) = \frac{1}{D} \sum_{k=0}^{D-1} X\left(\frac{\omega - 2\pi k}{D}\right)$$

9. Upsampling 

$$Y(\omega) = X(D\omega)$$

Transform Pairs

$$1. \delta[n] \xleftrightarrow{\text{DTFT}} 1$$

$$2. 1 \xleftrightarrow{\text{DTFT}} 2\pi \text{rep}_{2\pi}[\delta(\omega)]$$

$$3. e^{j\omega_0 n} \xleftrightarrow{\text{DTFT}} 2\pi \text{rep}_{2\pi}[\delta(\omega - \omega_0)]$$

$$4. \cos(\omega_0 n) \xleftrightarrow{\text{DTFT}} \pi \text{rep}_{2\pi}[\delta(\omega - \omega_0) + \delta(\omega + \omega_0)]$$

$$x[n] = \begin{cases} 1, & n = 0, 1, \dots, N-1 \\ 0, & \text{else} \end{cases} \xleftrightarrow{\text{DTFT}}$$

$$5. X(\omega) = \text{psinc}_N(\omega) e^{-j\omega(N-1)/2}$$

where $\text{psinc}_N(\omega) \triangleq \frac{\sin(\omega N / 2)}{\sin(\omega / 2)}$

Relation between CT and DT

1. Time Domain

$$x_d[n] = x_a(nT)$$

2. Frequency Domain

$$X_d(\omega_d) = f_s \text{rep}_{f_s}[X_a(f_a)] \Big|_{f_a = \frac{\omega_d f_s}{2\pi}}$$

$$\text{where } f_s = \frac{1}{T}$$

ZT

Forward transform

$$X(z) = \sum_{n=-\infty}^{\infty} x[n] z^{-n}$$

Transform Relations

1. Linearity

$$a_1 x_1[n] + a_2 x_2[n] \xleftrightarrow{\text{ZT}} a_1 X_1(z) + a_2 X_2(z)$$

2. Shifting

$$x[n - n_0] \xleftrightarrow{\text{ZT}} X(z) z^{-n_0}$$

3. Modulation

$$x[n] z_0^n \xleftrightarrow{\text{ZT}} X(z / z_0)$$

4. Multiplication by time index

$$n x[n] \xleftrightarrow{\text{ZT}} -z \frac{d}{dz} [X(z)]$$

5. Convolution

$$x[n] * y[n] \xleftrightarrow{\text{ZT}} X(z) Y(z)$$

6. Relation to DTFT

If $X_{\text{ZT}}(z)$ converges for $|z|=1$, then the DTFT of $x[n]$ exists and

$$X_{\text{DTFT}}(\omega) = X_{\text{ZT}}(z) \Big|_{z=e^{j\omega}}$$

Transform Pairs

$$1. \delta[n] \xleftrightarrow{\text{ZT}} 1, \quad \text{all } z$$

$$2. a^n u[n] \xleftrightarrow{\text{ZT}} \frac{1}{1 - az^{-1}}, \quad |z| > |a|$$

$$3. -a^n u[-n-1] \xleftrightarrow{\text{ZT}} \frac{1}{1 - az^{-1}}, \quad |z| < |a|$$

$$4. n a^n u[n] \xleftrightarrow{\text{ZT}} \frac{az^{-1}}{(1 - az^{-1})^2}, \quad |z| > |a|$$

$$5. -n a^n u[-n-1] \xleftrightarrow{\text{ZT}} \frac{az^{-1}}{(1 - az^{-1})^2}, \quad |z| < |a|$$

DFT

Forward transform

$$X[k] = \sum_{n=0}^{N-1} x[n] e^{-j2\pi kn/N}$$

Inverse transform

$$x[n] = \frac{1}{N} \sum_{k=0}^{N-1} X[k] e^{j2\pi kn/N}$$

Transform Relations

1. Linearity

$$a_1 x_1[n] + a_2 x_2[n] \xleftrightarrow{\text{DFT}} a_1 X_1[k] + a_2 X_2[k]$$

2. Shifting

$$x[n - n_0] \xleftrightarrow{\text{DFT}} X[k] e^{-j2\pi n_0 k/N}$$

3. Modulation

$$x[n] e^{j2\pi n k_0/N} \xleftrightarrow{\text{DFT}} X[k - k_0]$$

4. Reciprocity

$$X[n] \xleftrightarrow{\text{DFT}} N x[-k]$$

5. Parseval

$$\sum_{n=0}^{N-1} |x[n]|^2 = \frac{1}{N} \sum_{k=0}^{N-1} |X[k]|^2$$

6. Initial Value

$$X[0] = \sum_{n=0}^{N-1} x[n]$$

$$x[0] = \frac{1}{N} \sum_{k=0}^{N-1} X[k]$$

7. Periodicity

$$x[n + mN] = x[n] \quad \text{for all integers } m$$

$$X[k + lN] = X[k] \quad \text{for all integers } l$$

8. Relation to DTFT of a finite length sequence

Let $x_0[n] \neq 0$ only for $0 \leq n \leq N-1$

$$x_0[n] \xleftrightarrow{\text{DTFT}} X_0(\omega).$$

$$\text{Define } x[n] = \sum_{m=-\infty}^{\infty} x_0[n + mN],$$

$$x[n] \xleftrightarrow{\text{DFT}} X[k],$$

$$\text{then } X[k] = X_0(e^{j2\pi k/N}).$$

9. Periodic convolution

$$x[n] \otimes y[n] \xleftrightarrow{\text{DFT}} X[k]Y[k]$$

10. Product

$$x[n]y[n] \xleftrightarrow{\text{DFT}} \frac{1}{N} X[k] \otimes Y[k]$$

Transform Pairs

$$1. \quad \delta[n], 0 \leq n \leq N-1 \xleftrightarrow{\text{DFT}} 1, 0 \leq k \leq N-1$$

$$2. \quad 1, 0 \leq n \leq N-1 \xleftrightarrow{\text{DFT}} N\delta[k], 0 \leq k \leq N-1$$

$$3. \quad e^{j2\pi k_0 n/N}, 0 \leq n \leq N-1 \xleftrightarrow{\text{DFT}} N\delta[k - k_0], 0 \leq k \leq N-1$$

$$4. \quad \cos(2\pi k_0 n/N), 0 \leq n \leq N-1 \xleftrightarrow{\text{DFT}} \frac{N}{2} \{ \delta[k - k_0] + \delta[k - (N - k_0)] \}, 0 \leq k \leq N-1$$

$$5. \quad e^{j\omega_0 n}, n = 0, 1, \dots, N-1 \xleftrightarrow{\text{DFT}} \text{psinc}_N(2\pi k/N - \omega_0) e^{-j(2\pi k/N - \omega_0)(N-1)/2}$$

Random Signals

1. Probability density function $f_X(x)$

$$P\{a < X \leq b\} = \int_a^b f_X(x) dx$$

$$\int_{-\infty}^{\infty} f_X(x) dx = 1 \quad f_X(x) \geq 0$$

2. Probability distribution function $F_X(x)$

$$F_X(x) = \int_{-\infty}^x f_X(\xi) d\xi$$

$$f_X(x) = \frac{dF_X(x)}{dx}$$

$F_X(-\infty) = 0 \quad F_X(\infty) = 1 \quad F_X(x)$ is a non-decreasing function of x

Expectation Operator

$$E\{g(X)\} = \int_{-\infty}^{\infty} g(x) f_X(x) dx$$

1. Mean $g(x) = x$

2. 2nd moment $g(x) = x^2$

3. Variance $g(x) = (x - E\{X\})^2$

4. Relation between mean, 2nd moment, and variance

$$\sigma_X^2 = E\{X^2\} - (E\{X\})^2$$

Two Random Variables

1. Bivariate probability density function $f_{XY}(x, y)$

$$P\{a < X \leq b, c < Y \leq d\} = \int_a^b \int_c^d f_{XY}(x, y) dx dy$$

$$\int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f_{XY}(x, y) dx dy = 1 \quad f_{XY}(x, y) \geq 0$$

2. Marginal probability density functions $f_X(x)$ and $f_Y(y)$

$$f_X(x) = \int_{-\infty}^{\infty} f_{XY}(x, y) dy$$

$$f_Y(y) = \int_{-\infty}^{\infty} f_{XY}(x, y) dx$$

3. Linearity of expectation

$$E\{ag(X, Y) + bh(X, Y)\} = aE\{g(X, Y)\} + bE\{h(X, Y)\}$$

4. Correlation of X and Y

$$E\{XY\} = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} xy f_{XY}(x, y) dx dy$$

5. Covariance of X and Y

$$\begin{aligned} \sigma_{XY}^2 &= E\{(X - E\{X\})(Y - E\{Y\})\} \\ &= E\{XY\} - E\{X\}E\{Y\} \end{aligned}$$

6. Correlation coefficient of X and Y

$$\begin{aligned} \rho_{XY} &= \frac{\sigma_{XY}^2}{\sigma_X \sigma_Y} \\ 0 \leq |\rho_{XY}| &\leq 1 \end{aligned}$$

7. X and Y are independent if and only if

$$f_{XY}(x, y) = f_X(x)f_Y(y)$$

8. X and Y are uncorrelated if and only if

$$E\{XY\} = E\{X\}E\{Y\}$$

Independence implies uncorrelatedness. The converse is not true.

Discrete-time random signals

1. Autocorrelation function

$$r_{XX}[m, m+n] = E\{X[m]X[m+n]\}$$

$X[m]$ is wide-sense stationary if and only if mean is constant, and autocorrelation depends only on difference between arguments, i.e.

$$E\{X[n]\} = \mu_X$$

$$r_{XX}[n] = E\{X[m]X[m+n]\}$$

2. Cross-correlation function

$$r_{XY}[m, m+n] = E\{X[m]Y[m+n]\}$$

$X[m]$ and $Y[m]$ are jointly wide-sense stationary if and only if they are individually wide-sense stationary and their cross-correlation depends only on difference between arguments, i.e.

$$r_{XY}[n] = E\{X[m]Y[m+n]\}$$

3. Wide-sense stationary processes and linear systems.

Let $X[n]$ be wide-sense stationary, and suppose that

$$Y[n] = h[n] * X[n] = \sum_m h[n-m]X[m],$$

then $X[n]$ and $Y[n]$ are jointly wide-sense stationary, and

$$\begin{aligned} \mu_Y &= \mu_X \sum_m h[m] \\ r_{XY}[n] &= h[n] * r_{XX}[n] \\ r_{YY}[n] &= h[n] * r_{XY}[-n] \end{aligned}$$

Model for Speech

Our model for the speech waveform is given by

$$s[n] = v[n] * e[n],$$

where $s[n]$ is the speech waveform, $v[n]$ is the vocal tract response that typically contains one or more peaks corresponding to resonant frequencies, and $e[n]$ is the excitation provided by the glottis.

$$e[n] = \begin{cases} \sum_k \delta[n-kP], & \text{for a voiced phoneme,} \\ \text{white noise,} & \text{for an unvoiced phoneme.} \end{cases}$$

Here P is the pitch period in samples.

Short-Time Discrete Time Fourier Transform (STDTFT)

Two interpretations:

1. DTFT of windowed waveform centered at (fixed) n where $w[n]$ is the window function

$$S(\omega, n) = \sum_k s[k]w[n-k]e^{-j\omega k}$$

2. Response of narrowband filter centered at (fixed) frequency ω , after shifting to base-band. The impulse response of the narrowband filter is $h_\omega[n] = h_0[n]e^{-j\omega n}$. Here $h_0[n]$ is the impulse response of the base-band filter, which is equivalent to the window function $w[n]$ in the first interpretation. We thus have

$$S(\omega, n) = (h_\omega[n] * s[n])e^{+j\omega n}$$

The display of the 2-D image $|S(\omega, n)|$ as a function of ω and n is called a *spectrogram*. Let N be the length of the window function $w[n]$; and let P be the pitch period. If $N \gg P$, the spectrogram is narrowband. If $N \approx P$, the spectrogram is wideband.

Modulated Filter Bank

Consider an L-channel modulated filter bank with input $x[n]$ and output from the ℓ -th channel given by

$$y_\ell[n] = h_\ell[n] * x[n],$$

where

$$h_\ell[n] = h_0[n]e^{-j2\pi n\ell/L}, \ell = 0, \dots, L-1.$$

The output of the filter bank is formed by summing the outputs of all L channels

$$y[n] = \sum_{\ell=0}^{L-1} y_\ell[n]$$

A necessary and sufficient condition for perfect reconstruction, i.e. $y[n] \equiv x[n]$ is

that the baseband filter impulse response $h_0[n]$ satisfy

$$h_0[n] = \begin{cases} \frac{1}{L}, & n = 0 \\ 0, & n = kL \end{cases}.$$

There are no constraints on $h_0[n]$ for other values of n .

2D CS Signals and Operators

$$1. \text{rect}(x, y) = \begin{cases} 1, & |x|, |y| < 1/2 \\ 0, & |x|, |y| > 1/2 \end{cases}$$

$$2. \text{sinc}(x, y) = \frac{\sin(\pi x)}{\pi x} \frac{\sin(\pi y)}{\pi y}$$

$$3. \text{circ}(x, y) = \begin{cases} 1, & \sqrt{x^2 + y^2} < 1/2 \\ 0, & \sqrt{x^2 + y^2} > 1/2 \end{cases}$$

$$4. \text{jinc}(x, y) = \frac{J_1(\pi\sqrt{x^2 + y^2})}{2\sqrt{x^2 + y^2}}$$

$$5. \delta(x, y) = \lim_{\Delta \rightarrow 0} \frac{1}{\Delta^2} \text{rect}\left(\frac{x}{\Delta}, \frac{y}{\Delta}\right)$$

$$f(x, y) ** g(x, y) =$$

$$6. \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(x - \xi, y - \eta) g(\xi, \eta) d\xi d\eta$$

$$\text{rep}_{X,Y}[f(x, y)] =$$

$$7. \sum_{k=-\infty}^{\infty} \sum_{l=-\infty}^{\infty} f(x - kX, y - lY)$$

$$\text{comb}_{X,Y}[f(x, y)] =$$

$$8. \sum_{k=-\infty}^{\infty} \sum_{l=-\infty}^{\infty} f(kX, lY) \delta(x - kX, y - lY)$$

9. Separability

$$f(x, y) = g(x)h(y)$$

Properties of the CS Impulse

$$\int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} \delta(x, y) dx dy = 1$$

1. and $\delta(x, y) = 0, (x, y) \neq (0, 0)$

$$\int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} \delta(x - x_0, y - y_0) f(x, y) dx dy = f(x_0, y_0),$$

2. provided $f(x, y)$ is continuous at $(x, y) = (x_0, y_0)$

$$\delta(x - x_0, y - y_0) ** f(x, y) = f(x - x_0, y - y_0)$$

CSFT

Sufficient conditions for existence

$$\int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} |f(x, y)| dx dy < \infty$$

$$\text{or } \int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} |f(x, y)|^2 dx dy < \infty$$

Forward transform

$$F(u, v) = \int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} f(x, y) e^{-j2\pi(ux+vy)} dx dy$$

Inverse transform

$$f(x, y) = \int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} F(u, v) e^{j2\pi(ux+vy)} du dv$$

Transform Relations

1. Linearity

$$a_1 f_1(x, y) + a_2 f_2(x, y) \xleftrightarrow{\text{CSFT}}$$

$$a_1 F_1(u, v) + a_2 F_2(u, v)$$

2. Scaling and shifting

$$f\left(\frac{x-x_0}{a}, \frac{y-y_0}{b}\right) \xleftrightarrow{\text{CSFT}}$$

$$|ab| F(au, bv) e^{-j2\pi(ux_0+vy_0)}$$

3. Modulation

$$f(x, y) e^{j2\pi(u_0 x + v_0 y)} \xleftrightarrow{\text{CSFT}} F(u - u_0, v - v_0)$$

4. Reciprocity

$$F(x, y) \xleftrightarrow{\text{CSFT}} f(-u, -v)$$

5. Parseval

$$\int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} |f(x, y)|^2 dx dy = \int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} |F(u, v)|^2 du dv$$

6. Initial Value

$$F(0, 0) = \int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} f(x, y) dx dy$$

$$x(0, 0) = \int_{-\infty-\infty}^{\infty} \int_{-\infty-\infty}^{\infty} F(u, v) du dv$$

7. Convolution

$$f(x, y) ** g(x, y) \xleftrightarrow{\text{CSFT}} F(u, v) G(u, v)$$

8. Product

$$f(x, y) g(x, y) \xleftrightarrow{\text{CSFT}} F(u, v) ** G(u, v)$$

9. Transform of doubly periodic signal

$$\text{rep}_{X,Y}[f(x, y)] \xleftrightarrow{\text{CSFT}} \frac{1}{XY} \text{comb}_{\frac{1}{X}, \frac{1}{Y}}[F(u, v)]$$

10. Transform of sampled signal

$$\text{comb}_{X,Y}[f(x, y)] \xleftrightarrow{\text{CSFT}} \frac{1}{XY} \text{rep}_{\frac{1}{X}, \frac{1}{Y}}[F(u, v)]$$

11. Transform of separable signal

$$g(x) h(y) \xleftrightarrow{\text{CSFT}} G(u) H(v)$$

Transform Pairs

$$1. \text{rect}(x, y) \overset{\text{CSFT}}{\leftrightarrow} \text{sinc}(u, v)$$

$$2. \text{circ}(x, y) \overset{\text{CSFT}}{\leftrightarrow} \text{jinc}(u, v)$$

$$3. \delta(x, y) \overset{\text{CSFT}}{\leftrightarrow} 1 \text{ and } 1 \overset{\text{CSFT}}{\leftrightarrow} \delta(u, v)$$

$$4. e^{j2\pi(u_0x+v_0y)} \overset{\text{CSFT}}{\leftrightarrow} \delta(u-u_0, v-v_0)$$

$$\cos[2\pi(u_0x+v_0y)] \overset{\text{CTFT}}{\leftrightarrow}$$

$$5. \frac{1}{2} \{ \delta(u-u_0, v-v_0) + \delta(u+u_0, v+v_0) \}$$

DSFT

Forward transform

$$X(\mu, \nu) = \sum_m \sum_n x[m, n] e^{-j(m\mu + n\nu)}$$

Inverse transform

$$x[m, n] = \frac{1}{(2\pi)^2} \int_{-\pi}^{\pi} \int_{-\pi}^{\pi} X(\mu, \nu) e^{j(m\mu + n\nu)} d\mu d\nu$$

Computed Tomography

1. Radon Transform (Projection)

$$p_{\theta}(t) = \iint f(x, y) \delta(x \cos \theta + y \sin \theta - t) dx dy$$

2. Fourier Slice Theorem

$$\begin{aligned} P_{\theta}(\rho) &= \int p_{\theta}(t) e^{-j2\pi \rho t} dt \\ &= F(\rho \cos \theta, \rho \sin \theta) \end{aligned}$$

Miscellaneous

1. Geometric Series

$$\sum_{n=0}^{N-1} z^n = \frac{1-z^N}{1-z}$$

2. N roots $z_k, k=0, \dots, N-1$, of a complex constant u_0 , i.e. N solutions to

$$\begin{aligned} z^N - u_0 &= 0 \\ z_k &= |u_0|^{1/N} e^{j(2\pi k + \angle u_0)/N}, k=0, \dots, N-1 \end{aligned}$$

3. Trigonometric Identities

$$\sin(\alpha \pm \beta) = \sin \alpha \cos \beta \pm \cos \alpha \sin \beta$$

$$\cos(\alpha \pm \beta) = \cos \alpha \cos \beta \mp \sin \alpha \sin \beta$$

$$\sin(2\alpha) = 2 \sin \alpha \cos \alpha$$

$$\cos(2\alpha) = \cos^2 \alpha - \sin^2 \alpha$$

$$\sin^2 \alpha = \frac{1}{2} - \frac{1}{2} \cos(2\alpha)$$

$$\cos^2 \alpha = \frac{1}{2} + \frac{1}{2} \cos(2\alpha)$$

$$\sin \alpha \sin \beta = \frac{1}{2} [\cos(\alpha - \beta) - \cos(\alpha + \beta)]$$

$$\cos \alpha \cos \beta = \frac{1}{2} [\cos(\alpha - \beta) + \cos(\alpha + \beta)]$$

$$\sin \alpha \cos \beta = \frac{1}{2} [\sin(\alpha + \beta) + \sin(\alpha - \beta)]$$

$$\cos \alpha \sin \beta = \frac{1}{2} [\sin(\alpha + \beta) - \sin(\alpha - \beta)]$$