

**NAME:**  
**EE301 Signals and Systems**  
**Exam 3**

**NAME**  
**In-Class Exam**  
**Tuesday, Apr. 23, 2015**

## **Cover Sheet**

Test Duration: 75 minutes.

Coverage: Chaps. 5,7

Open Book but Closed Notes.

One 8.5 in. x 11 in. crib sheet

Calculators NOT allowed.

All work should be done on the sheets provided.

You must show all work for each problem to receive full credit.

For Problem 4, plot your answers on the graphs provided.

**Problem 1. Short answer questions.**

- (a) Briefly write and explain one of the main advantages of digital over analog, in terms of storage, transmission, and processing.

- (b) If you sample at a rate  $\omega_s$  in terms of radians/sec, what discrete-time frequency is the analog frequency  $\frac{\omega_s}{3}$  mapped to?

- (a) The DT signal  $x[n]$  is obtained by sampling the sinewave  $x_{a_1}(t) = \cos(10t + \phi)$ , where the value of the phase is  $\phi = \pi/\sqrt{2}$ , at a rate of  $\omega_s = 30$  radians/sec. Specify the frequency  $\omega_{a_2}$  of another sinewave  $x_{a_2}(t) = \cos(\omega_{a_2}t)$  at a higher frequency that will yield the exact same DT signal  $x[n]$  when sampled at the same rate,  $\omega_s = 30$  radians/sec.

**Problem 2 (a).** The signal  $x_a(t) = \{u(t+2) - u(t-2)\}$  is sampled every  $T_s = 0.5$  seconds to form  $x[n] = x_a(nT_s)$ , where, again,  $T_s$  is a half of a second. Determine a closed-form expression for the DTFT  $X(\omega)$  of the  $x[n]$  thus obtained. Assume that the signal is turned on equal to 1 at both ends (edges), that is, at both  $t = -2$  secs and  $t = +2$  secs.

$$x[n] = x_a(nT_s) \quad \text{where: } T_s = 0.5 \text{ secs} \quad \text{and} \quad x_a(t) = \{u(t+2) - u(t-2)\}$$

**Problem 2 (b).** The signal  $x_a(t) = t \{u(t+2) - u(t-2)\}$  is sampled every  $T_s = 0.5$  seconds to form  $x[n] = x_a(nT_s)$ , where, again,  $T_s$  is a half of a second. Determine a closed-form expression for the DTFT  $X(\omega)$  of the  $x[n]$  thus obtained. Assume that the signal is turned on equal to 1 at both ends (edges), that is, at both  $t = -2$  secs and  $t = +2$  secs.

$$x[n] = x_a(nT_s) \quad \text{where: } T_s = 0.5 \text{ secs} \quad \text{and} \quad x_a(t) = t \{u(t+2) - u(t-2)\}$$

**Problem 3.** Consider the input signal  $x_p(t)$  below.

$$x_0(t) = e^{-j25t} + e^{-j20t} + e^{-j15t} + e^{-j10t} + e^{-j5t} + 1 + e^{j5t} + e^{j10t} + e^{j15t} + e^{j20t} + e^{j25t}$$

This signal is first input to an analog filter with impulse response

$$h_{LP}(t) = \frac{\pi}{5} \left\{ \frac{\sin(5t)}{\pi t} \right\}^2 2j \sin(10t)$$

to form  $x(t) = x_0(t) * h_{LP}(t)$ , and then  $x(t)$  is sampled at a rate of  $\omega_s = 40$  to form  $x[n]$ , so that the time between samples is  $T_s = \frac{2\pi}{40}$ . The DT signal  $x[n]$  thus obtained is then input to a DT LTI system with impulse response

$$h[n] = e^{j\pi n} \left\{ \frac{\sin\left(\frac{5\pi}{8}n\right)}{\pi n} \right\} \quad (1)$$

Show all work. Write your expression for the output  $y[n] = x[n] * h[n]$  in the space below. Plot both the Fourier Transform of  $h_{LP}(t)$  and the DTFT of  $h[n]$  to help solve the problem, but since the input is a sum of sinewaves, it is not necessary to plot the Fourier Transform of  $x_0(t)$  or the DTFT of the sampled signal  $x[n]$ .

**Problem 3.** You can continue your work for 3 here.

**Workout Problem 4.** Consider the continuous-time signal  $x_a(t)$  below. Note that the multiplication by the scalar  $j$  is included to make the Fourier Transform  $X_a(\omega)$  be purely real-valued, and the multiplication by the scalar  $T_s$  is intended to offset the amplitude-scaling by the sampling rate  $F_s = \frac{1}{T_s}$  that inherently occurs in the process of sampling.

$$x_a(t) = T_s \frac{\pi}{5} \left\{ \frac{\sin(5t)}{\pi t} \right\}^2 2j \sin(10t)$$

- (a) A discrete-time signal is created by sampling  $x_a(t)$  according to  $x[n] = x_a(nT_s)$  for  $T_s = \frac{2\pi}{40}$ . Plot the DTFT of  $x[n]$ ,  $X(\omega)$ , over  $-\pi < \omega < \pi$ . Show your work on this page and the next page, and do your plot in the space provided on the next page.
- (b) Repeat part (a) for  $T_s = \frac{2\pi}{25}$ . Plot the new DTFT of  $x[n]$ ,  $X(\omega)$ , over  $-\pi < \omega < \pi$ . Show your work and do your plot in the space provided on the sheets attached.

Plot your answer to Problem 4 (a) here. Show work .

Plot your answer to Problem 4 (b) on next page .





