

Name:

**Final Exam**  
**ECE301 Signals and Systems Wednesday, May 6, 2015**

## **Cover Sheet**

**Write your name on this page and every page to be safe.**

Test Duration: 120 minutes.

Coverage: Comprehensive

Open Book but Closed Notes. Three two-sided handwritten sheets.

Calculators NOT allowed.

This test contains **four** problems, each with multiple parts.

You have to draw your own plots.

You must show all work for each problem to receive full credit.

**Good luck! It was great having you in class this semester!**

**Have a great Summer!**

**Problem 1.** Using the Z-Transform, determine the output of the system

$$y[n] = \alpha y[n - 1] + x[n]$$

for the input  $x[n] = \beta^n u[n]$ . You must use the Z-Transform to solve this problem, i.e., use basic Z-Transform properties and a basic Z-Transform pair plus partial fraction expansion to ultimately determine the output  $y[n]$ . You are given that  $|\alpha| < 1$  and  $|\beta| < 1$ .

Show your work and plots for Problem 1 here.

**Problem 2.**

The rectangular pulse  $x_{in}(t) = \{u(t) - u(t - 1)\}$  of duration 1 sec is input to the following integrator

$$x_a(t) = 3 \int_{t-2}^t x_{in}(\tau) d\tau - 3 \int_{t-5}^{t-3} x_{in}(\tau) d\tau$$

The output  $x_a(t)$  is sampled every  $T_s = 1/3$  seconds to form  $x[n] = x_a(nT_s)$ . The sampling rate is  $f_s = 3$  samples/sec. Show work. Clearly label and write your final answer in the space provided on the next few pages.

- (a) Do a stem plot of the DT signal  $x[n]$ , or you can simply write the numbers that comprise  $x[n]$  (indicate with an arrow where the  $n = 0$  value is.)
- (b) The Discrete-Time (DT) signal  $x[n]$ , created as described above, is input to the DT system described by the difference equation below:

$$y[n] = x[n] - x[n - 1]$$

- (i) First, determine the impulse response  $h[n]$  for this system.
- (ii) Determine and plot the output  $y[n]$  by convolving the input  $x[n]$  defined above with the impulse response  $h[n]$ . Show all work in the space provided. Do the stem-plot for  $y[n]$  on the graph provided on the page after next.

Show your work and plots for Problem 2 here.

Show your work and plots for Problem 2 here.

**Problem 3 (a).** Consider an analog signal  $x_a(t)$  with maximum frequency (bandwidth)  $\omega_M = 40$  rads/sec. That is, the Fourier Transform of the analog signal  $x_a(t)$  is exactly zero for  $|\omega| > 40$  rads/sec. This signal is sampled at a rate  $\omega_s = 100$  rads/sec., where  $\omega_s = 2\pi/T_s$  such the time between samples is  $T_s = \frac{2\pi}{100}$  sec. This yields the discrete-time sequence

$$x[n] = x_a(nT_s) = \left\{ \frac{\pi \sin\left(\frac{\pi}{10}n\right) \sin\left(\frac{3\pi}{10}n\right)}{5 \pi n T_s \pi n T_s} \right\} 2j \sin\left(\frac{2\pi}{5}n\right) \quad \text{where: } T_s = \frac{2\pi}{100}$$

A reconstructed signal is formed from the samples above according to the formula below. Determine a simple, closed-form expression for the reconstructed signal  $x_r(t)$ . Show work.

$$x_r(t) = \sum_{n=-\infty}^{\infty} x[n]h(t - nT_s) \quad \text{where: } T_s = \frac{2\pi}{100} \quad \text{and} \quad h(t) = T_s \frac{\pi \sin(10t) \sin(50t)}{10 \pi t \pi t}$$

**Problem 3 (b).** Consider the SAME analog signal  $x_a(t)$  with maximum frequency (bandwidth)  $\omega_M = 40$  rads/sec. This signal is sampled at the same rate  $\omega_s = 100$  rads/sec., but is reconstructed with a different lowpass interpolating filter according to the formula below. Does this achieve perfect reconstruction, that is, does  $x_r(t) = x_a(t)$ ? **For this part, you do not need to determine  $x_r(t)$ , just need to explain whether  $x_r(t) = x_a(t)$  or not.**

$$x_r(t) = \sum_{n=-\infty}^{\infty} x[n]h(t - nT_s) \quad \text{where: } T_s = \frac{2\pi}{100} \quad \text{and} \quad h(t) = T_s \frac{1}{2} \left\{ \frac{\sin(40t)}{\pi t} + \frac{\sin(60t)}{\pi t} \right\}$$

**Problem 3 (c).** Consider the SAME analog signal  $x_a(t)$  with maximum frequency (bandwidth)  $\omega_M = 40$  rads/sec. This signal is sampled at the same rate  $\omega_s = 100$  rads/sec., but is reconstructed with a different lowpass interpolating filter according to the formula below. Does this achieve perfect reconstruction, that is, does  $x_r(t) = x_a(t)$ ? **For this part, you do not need to determine  $x_r(t)$ , just need to explain whether  $x_r(t) = x_a(t)$  or not.**

$$x_r(t) = \sum_{n=-\infty}^{\infty} x[n]h(t - nT_s) \quad \text{where: } T_s = \frac{2\pi}{100} \quad \text{and} \quad h(t) = T_s \frac{1}{2} \left\{ \frac{\sin(45t)}{\pi t} + \frac{\sin(55t)}{\pi t} \right\}$$

**Show all your work for Prob. 3, parts (a)-(b)-(c) on next page.**

Show your work for Prob. 3, parts (a)-(b)-(c) below.



**Problem 3 (d).** Consider an analog signal  $x_a(t)$  with maximum frequency (bandwidth)  $\omega_M = 40$  rads/sec. That is, the Fourier Transform of the analog signal  $x_a(t)$  is exactly zero for  $|\omega| > 40$  rads/sec. This signal is sampled at a rate  $\omega_s = 80$  rads/sec., where  $\omega_s = 2\pi/T_s$  such the time between samples is  $T_s = \frac{2\pi}{80}$  sec. This yields the discrete-time sequence

$$x[n] = x_a(nT_s) = \left\{ \frac{\pi \sin\left(\frac{\pi}{8}n\right) \sin\left(\frac{3\pi}{8}n\right)}{5 \pi n T_s} \right\} 2j \sin\left(\frac{\pi}{2}n\right) \quad \text{where: } T_s = \frac{2\pi}{80}$$

A reconstructed signal is formed from the samples above according to the formula below. Determine a simple, closed-form expression for the reconstructed signal  $x_r(t)$ . Show work.

$$x_r(t) = \sum_{n=-\infty}^{\infty} x[n]h(t - nT_s) \quad \text{where: } T_s = \frac{2\pi}{80} \quad \text{and} \quad h(t) = T_s \frac{\sin(40t)}{\pi t}$$

**Problem 3 (e).** Consider the SAME analog signal  $x_a(t)$  with maximum frequency (bandwidth)  $\omega_M = 40$  rads/sec. This signal is sampled at the same rate  $\omega_s = 80$  rads/sec., but reconstructed with a different lowpass interpolating filter according to the formula below. Does this achieve perfect reconstruction, that is, does  $x_r(t) = x_a(t)$ ? **For this part, you do not need to determine  $x_r(t)$ , just need to explain whether  $x_r(t) = x_a(t)$  or not.**

$$x_r(t) = \sum_{n=-\infty}^{\infty} x[n]h(t - nT_s) \quad \text{where: } T_s = \frac{2\pi}{80} \quad \text{and} \quad h(t) = T_s \left\{ \frac{\pi \sin(5t) \sin(40t)}{5 \pi t \pi t} \right\}$$

**Problem 3 (f).** Consider the SAME analog signal  $x_a(t)$  with maximum frequency (bandwidth)  $\omega_M = 40$  rads/sec. This signal is sampled at the same rate  $\omega_s = 80$  rads/sec., but reconstructed with a different lowpass interpolating filter according to the formula below. Does this achieve perfect reconstruction, that is, does  $x_r(t) = x_a(t)$ ? **For this part, you do not need to determine  $x_r(t)$ , just need to explain whether  $x_r(t) = x_a(t)$  or not.**

$$x_r(t) = \sum_{n=-\infty}^{\infty} x[n]h(t - nT_s) \quad \text{where: } T_s = \frac{2\pi}{80} \quad \text{and} \quad h(t) = T_s \frac{1}{2} \left\{ \frac{\sin(40t)}{\pi t} + \frac{\sin(10t)}{\pi t} \right\}$$

**Show all your work for Prob. 3, parts (d)-(e)-(f) on next page.**

Show your work for Prob. 3, parts (d)-(e)-(f) below.

**Problem 3 (g).** Consider an analog signal  $x_a(t)$  with maximum frequency (bandwidth)  $\omega_M = 40$  rads/sec. This signal is sampled at a rate  $\omega_s = 50$  rads/sec., where  $\omega_s = 2\pi/T_s$  such the time between samples is  $T_s = \frac{2\pi}{50}$  sec, yielding the following discrete-time sequence:

$$x[n] = x_a(nT_s) = \left\{ \frac{\pi \sin\left(\frac{\pi}{5}n\right) \sin\left(\frac{3\pi}{5}n\right)}{5 \pi n T_s} \right\} 2j \sin\left(\frac{4\pi}{5}n\right) \quad \text{where: } T_s = \frac{2\pi}{50}$$

A reconstructed signal is formed from the samples above according to the formula below. Determine a closed-form expression for the reconstructed signal  $x_r(t)$ . Show all work.

$$x_r(t) = \sum_{n=-\infty}^{\infty} x[n]h(t - nT_s) \quad \text{where: } T_s = \frac{2\pi}{50} \quad \text{and} \quad h(t) = T_s \frac{\sin(25t)}{\pi t}$$

**Problem 3 (h).** Consider the SAME analog signal  $x_a(t)$  with maximum frequency (bandwidth)  $\omega_M = 40$  rads/sec. This signal is sampled at the same rate  $\omega_s = 50$  rads/sec., where  $\omega_s = 2\pi/T_s$  and the time between samples is  $T_s = \frac{2\pi}{50}$  sec, but at a different starting point. This yields the Discrete-Time  $x[n]$  signal below:

$$x_\epsilon[n] = x_a(nT_s + 0.5T_s) = \left\{ \frac{\pi}{5} \right\} \left\{ \frac{\sin\left(\frac{\pi}{5}(n + 0.5)\right) \sin\left(\frac{3\pi}{5}(n + 0.5)\right)}{\pi(n + 0.5)T_s} \right\} 2j \sin\left(\frac{4\pi}{5}(n + 0.5)\right)$$

A reconstructed signal is formed from the samples above according to the formula below. Determine a simple, closed-form expression for the reconstructed signal  $x_r(t)$ . *Hint:* before you do a lot of work, look at the interpolating lowpass filter being used below.

$$x_r(t) = \sum_{n=-\infty}^{\infty} x_\epsilon[n]h(t - (n + 0.5)T_s) \quad \text{where: } T_s = \frac{2\pi}{50} \quad \text{and} \quad h(t) = T_s \frac{\sin(10t)}{\pi t}$$

**Show your work for Prob. 3, parts (g)-(h) on next page.**

Show all your work for Prob. 3, parts (g)-(h) on this page.

**Problem 4.** For each part: show all work, state which Fourier Transform pairs and/or properties you are using, and clearly indicate your final answer. Use the result below:

$$\int_{-\infty}^{\infty} e^{-\frac{(x-m)^2}{2\sigma^2}} dx = \sqrt{2\pi} \sigma$$

**Problem 4 (a).** The Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}} e^{-\frac{t^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , is multiplied by a complex-valued sinewave to form  $y(t) = e^{j3t}x(t)$ . Find the numerical value of  $E = \frac{1}{2\pi} \int_{-\infty}^{\infty} |Y(\omega)|^2 d\omega$ .

**Problem 4 (b).** The Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}} e^{-\frac{t^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , is time-shifted to form  $y(t) = x(t - 3)$ . Find the numerical value of  $E = \frac{1}{2\pi} \int_{-\infty}^{\infty} |Y(\omega)|^2 d\omega$ .

**Problem 4 (c).** The Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , is differentiated to form  $y(t) = \frac{d}{dt}x(t)$ . Find the numerical value of  $A = \int_{-\infty}^{\infty} y(t)dt$ .

**Problem 4 (d).** The Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , is multiplied by  $t$  to form  $y(t) = tx(t)$ . Find the numerical value of  $A = \int_{-\infty}^{\infty} y(t)dt$ . Show all work, state which Fourier Transform pairs and/or properties you are using, and clearly indicate your final answer.

**Problem 4 (e).** The Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , is compressed in time by a factor of 2 to form  $y(t) = x(2t)$ . Find the numerical value of the energy  $E = \int_{-\infty}^{\infty} y^2(t)dt$ .

**Problem 4 (f).** The Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , is input to an LTI system with a Gaussian shaped impulse response,  $h(t) = \frac{1}{\sigma_2\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_2^2}}$ , with  $\sigma_2^2 = 4^2$ . Determine a simple, closed-form expression for the output  $y(t) = x(t) * h(t)$ .

**Problem 4 (g).** The Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , is input to an LTI system with a Gaussian shaped impulse response,  $h(t) = \frac{1}{\sigma_2\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_2^2}}$ , with  $\sigma_2^2 = 4^2$ . Determine the numerical value of the area,  $A = \int_{-\infty}^{\infty} y(t)dt$ , under the output  $y(t) = x(t) * h(t)$ .

**Problem 4 (h).** The Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , is input to an LTI system with a Gaussian shaped impulse response,  $h(t) = \frac{1}{\sigma_2\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_2^2}}$ , with  $\sigma_2^2 = 4^2$ . Determine the numerical value of the energy  $E = \int_{-\infty}^{\infty} y^2(t)dt$  of the output  $y(t) = x(t) * h(t)$ .



**Problem 4 (i).** The Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}}e^{-\frac{(t-2)^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , is input to an LTI system with a Gaussian shaped impulse response,  $h(t) = \frac{1}{\sigma_2\sqrt{2\pi}}e^{-\frac{(t-3)^2}{2\sigma_2^2}}$ , with  $\sigma_2^2 = 4^2$ . Determine the numerical value of the energy  $E = \int_{-\infty}^{\infty} y^2(t)dt$  of the output  $y(t) = x(t)*h(t)$ .

**Problem 4 (j).** The signal  $z(t) = x(t)y(t)$  is the PRODUCT of the Gaussian pulse  $x(t) = \frac{1}{\sigma_1\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_1^2}}$ , with  $\sigma_1^2 = 3^2$ , and the Gaussian pulse  $y(t) = \frac{1}{\sigma_2\sqrt{2\pi}}e^{-\frac{t^2}{2\sigma_2^2}}$ , with  $\sigma_2^2 = 4^2$ . Determine a simple expression for the Fourier Transform,  $Z(\omega)$ , of  $z(t) = x(t)y(t)$ .