

TABLE 5.2 BASIC DISCRETE-TIME FOURIER TRANSFORM PAIRS

| Signal  | Fourier Transform  | Fourier Series Coefficients (if periodic)  |
|---|--|--|
| $\sum_{k=-N}^{+\infty} a_k e^{jk(2\pi/N)n}$   | $2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$   | $a_k$  |
| $e^{j\omega_0 n}$   | $2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - \omega_0 - 2\pi l)$   | (a) $\omega_0 = \frac{2\pi m}{N}$<br>$a_k = \begin{cases} 1, & k = m, m \pm N, m \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$<br>(b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic   |
| $\cos \omega_0 n$   | $\pi \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) + \delta(\omega + \omega_0 - 2\pi l)\}$                                   | (a) $\omega_0 = \frac{2\pi m}{N}$<br>$a_k = \begin{cases} \frac{1}{2}, & k = \pm m, \pm m \pm N, \pm m \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$<br>(b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic   |
| $\sin \omega_0 n$   | $\frac{\pi}{j} \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) - \delta(\omega + \omega_0 - 2\pi l)\}$                         | (a) $\omega_0 = \frac{2\pi r}{N}$<br>$a_k = \begin{cases} \frac{1}{2j}, & k = r, r \pm N, r \pm 2N, \dots \\ -\frac{1}{2j}, & k = -r, -r \pm N, -r \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$<br>(b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic |
| $x[n] = 1$  | $2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - 2\pi l)$  | $a_k = \begin{cases} 1, & k = 0, \pm N, \pm 2N, \dots \\ 0, & \text{otherwise} \end{cases}$  |
| Periodic square wave<br>$x[n] = \begin{cases} 1, &  n  \leq N_1 \\ 0, & N_1 <  n  \leq N/2 \end{cases}$<br>and<br>$x[n+N] = x[n]$ | $2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$   | $a_k = \frac{\sin[(2\pi k/N)(N_1 + \frac{1}{2})]}{N \sin[2\pi k/2N]}, k \neq 0, \pm N, \pm 2N, \dots$<br>$a_k = \frac{2N_1 + 1}{N}, k = 0, \pm N, \pm 2N, \dots$   |
| $\sum_{k=-\infty}^{+\infty} \delta[n - kN]$   | $\frac{2\pi}{N} \sum_{k=-\infty}^{+\infty} \delta\left(\omega - \frac{2\pi k}{N}\right)$   | $a_k = \frac{1}{N}$ for all $k$  |
| $a^n u[n],  a  < 1$   | $\frac{1}{1 - ae^{-j\omega}}$  | —  |
| $x[n] = \begin{cases} 1, &  n  \leq N_1 \\ 0, &  n  > N_1 \end{cases}$  | $\frac{\sin[\omega(N_1 + \frac{1}{2})]}{\sin(\omega/2)}$   | —  |
| $\frac{\sin W_n}{\pi n} = \frac{W}{\pi} \operatorname{sinc}\left(\frac{Wn}{\pi}\right)$<br>$0 < W < \pi$                          | $X(\omega) = \begin{cases} 1, & 0 \leq  \omega  \leq W \\ 0, & W <  \omega  \leq \pi \end{cases}$<br>X( $\omega$ ) periodic with period $2\pi$ | —  |
| $\delta[n]$   | 1  | —  |
| $u[n]$  | $\frac{1}{1 - e^{-j\omega}} + \sum_{k=-\infty}^{+\infty} \pi \delta(\omega - 2\pi k)$  | —  |
| $\delta[n - n_0]$   | $e^{-j\omega n_0}$   | —  |
| $(n+1)a^n u[n],  a  < 1$  | $\frac{1}{(1 - ae^{-j\omega})^2}$  | —  |
| $\frac{(n+r-1)!}{n!(r-1)!} a^n u[n],  a  < 1$   | $\frac{1}{(1 - ae^{-j\omega})^r}$  | —  |